SAFETY SIMPLIFIED TO THE MAX

Making safety transparent and understandable

In order to implement safety controls, it is essential to begin taking safety into consideration at the design stage. We offer safety systems that incorporate the latest sensing and control technologies combined with safety design, consulting services to ensure optimum machine and equipment safety and secure a safe production environment.



Understand safety in minutes and ask for your own free safety guide at: www.ce-safety.info

Safety – Table of contents

Control- and S	ignalling devices	14
Product overview		308
Selection table		310
Standard	A16	312
pushbutton switches	A22	314
Emergency stop	A165E	316
pushbutton switches	A22E	317
Rope pull emergency stop switches	ER-series	318
Signalling devices	MP/MPS	321
	LME	323
	LU5	325
	LU7	329

Safety limit switches		
Product overview		332
Selection table		335
Safety limit switch with metal housing	D4BN	336
Safety limit switch with plastic housing	D4N	338
Safety door hinge switch	D4NH	340
Safety limit switch with manual reset	D4NR	341

Safety door switches 16			
Product overview		342	
Selection table		344	
Guard-lock safety	D4NL	347	
door switch	D4GL	348	
	D4BL	349	
Safety door switches	D4NS	350	
	D4BS	351	
Non-contact switches	F3S-TGR-N_C	352	
	F3S-TGR-N_R	354	
	D40A/G9SX-NS	380	

Safety sensors 17				
Product overview		356		
Selection table		358		
Category-2 safety light curtain	F3S-B	360		
Category 4/2 safety light curtain	MS4800/2800	361		
Category-4 safety light curtain/multi-beam safety sensor	F3SN-A	363		
Multi-beam safety sensor	F3S-TGR-CL	365		
Safety laser scanner	0S32C	369		
Single-beam safety sensor in compact housing	E3FS	372		
Safety light curtain controller with integrated muting function	F3SP-U4P	373		

Safety control systems 1				
Product overview		374		
Selection table		376		
Slim-size safety unit	G9SB	378		
Expandable safety relay unit	G9SA	379		
Compact non-contact door switch/flexible safety unit	D40A/G9SX-NS	380		
Safety guard switching unit	G9SX-GS/A4EG	382		
Flexible safety unit	G9SX	384		
Standstill monitoring unit	G9SX-SM	385		
Limited speed monitoring unit	G9SX-LM	386		
Standalone safety controller	G9SP-N_	388		
Safety network controller	NE1A-SCPU_	390		
DeviceNet safety I/O terminal block family	DST1-ID/-MD/-MRD	391		
Relays with forcibly guided contacts	G7SA	393		
Reliability data of Omron cor	nnonante	304		


INTERACT WITH YOUR MACHINE

Patlite Signal towers

Machines that are stopped during production are creating extra cost, our signal towers are used to show this status and guide workers to service the machines efficiently, minimizing downtime and production loss.


- · LED technology
- · Optional sound system
- 30 mm, 50 mm, 60 mm and 70 mm diameter
- · Modular and monolithic systems









Selection table





Control- and Signalling devices







16 mm pushbutton switch

These sub-assembled pushbutton switches have a modular construction: pushbutton + case + lamp (if applicable) + switch. A16 is a nut-mounted pushbutton switch with a short mounting depth of less than 28.5mm below panel.

- Wide variety of control and signal devices: lighted, non-lighted and buzzer
- Quick and easy assembly, snap-in switch
- Wide range of switching capacity from standard load to micro load
- High reliability, IP65
- UL, cUL, CSA and VDE approved, conforms to EN60947-5-1 and IEC947-5-1

Ordering information

Туре	Colour	Order code		
		Degree of protection: Oil-resistant IP65		
		Rectangular	Square	Round
Non-lighted	Red	A165L-JR	A165L-AR	A165L-TR
LED	Yellow	A165L-JY	A165L-AY	A165L-TY
Incandescent lamp	Pure yellow	A165L-JPY	A165L-APY	A165L-TPY
	White	A165L-JW	A165L-AW	A165L-TW
	Blue	A165L-JA	A165L-AA	A165L-TA
Non-lighted	Black	A165L-JB	A165L-AB	A165L-TB
LED	Green	A165L-TGY	A165L-AGY	A165L-TGY
Non-lighted/incandescent lamp	Green	A165L-JG	A165L-AG	A165L-TG

Cases

		,,,					
	Appearance	Classification		Order code			
				Oil-resistant IP65			
	Momentary operation	Momentary operation Rectangular (2-way guard) A165-CJM Square A165-CAM	A165-CJM				
			A165-CAM				
			Round	A165-CTM			
	Alternate operation	Rectangular (2-way guard)	A165-CJA				
		Square	A165-CAA				
			Round	A165-CTA			

Switches

Appearance	Classification				Order code
	Lighted/ non-lighted	microload (common use)	SPDT	Solder terminal	A16-1
TONE	(common use)		DPDT		A16-2
			SPDT	PCB terminal	A16-1P
*			DPDT		A16-2P
			DPDT	Screw- less clamp	A16-2S

Lamps

2411/90				
Colour	Order code			
	5 VDC	12 VDC	24 VDC	
Red	A16-5DSR	A16-12DSR	A16-24DSR	
Yellow	A16-5DSY	A16-12DSY	A16-24DSY	
Green	A16-5DSG	A16-12DSG	A16-24DSG	
White *1	A16-5DSW	A16-12DSW	A16-24DSW	
Blue	A16-5DA	A16-12DA	A16-24DA	
	5 VAC/VDC	12 VAC/VDC	24 VAC/VDC	
amp	A16-5	A16-12	A16-24	
	Red Yellow Green White *1 Blue	5 VDC Red A16-5DSR Yellow A16-5DSY Green A16-5DSG White *1 A16-5DSW Blue A16-5DA 5 VAC/VDC	5 VDC 12 VDC Red A16-5DSR A16-12DSR Yellow A16-5DSY A16-12DSY Green A16-5DSG A16-12DSG White *1 A16-5DSW A16-12DSW Blue A16-5DA A16-12DA 5 VAC/VDC 12 VAC/VDC	

^{*1} Use the white LED together with white or pure yellow pushbuttons.

Switches with reduced voltage lighting

Appearance	Classi	fication			Order code	
40	100 V Standard load/ microload (common use)	microload	Solder terminal	A16-T1-1		
		(common use)	DPDT		A16-T1-2	
	100 V	100 V		DPDT	Screw-less clamp	A16-T1-2S
	200 V				A16-T2-2S	



Accessories

Name	Appearance	Classification	Remarks	Order code
Switch guards	ritch guards	For rectangular models	Cannot be used with the dust cover	A16ZJ-5050
		For square and round models		A16ZA-5050
Dust covers		For rectangular models	Cannot be used with the switch guard	A16ZJ-5060
		For square models		A16ZA-5060
		For round models		A16ZT-5060
Panel plugs		For rectangular models	Used for covering the panel cutouts for future panel expansion	A16ZJ-3003
		For square models		A16ZA-3003
		For round models		A16ZT-3003

Allowable operating frequency	Mechanical	Momentary operation: 120 operations/minute max. Alternate operation: 60 operations/minute max.		
	Electrical	20 operations/minute max.		
Durability	Mechanical	Momentary operation: 2,000,000 operations min. Alternate operation: 200,000 operations min.		
	Electrical	100,000 operations min.		
Ambient temperature		Operating: -10 to 55°C (with no icing or condensation) Storage: -25 to 65°C (with no icing or condensation)		
Weight		Approx. 10 g (in the case of a lighted DPDT switch with solder terminals)		
, ,		Round/square: 18x18x28.5 rectangular: 18x24x28.5		

Operating characteristics	Pushbutton switch	
	Oil-resistant IP65	
	SPDT	DPDT
Operating force (OF) max.	2.94 N	4.91 N
Releasing force (RF) min.	0.29 N	
Total travel (TT)	Approx. 3 mm	
Pretravel (PT) max.	2.5 mm	
Lock stroke (LTA) min.	0.5 mm	

Item		Screw-less clamp				
Recommended wire size		0.5 mm ² twisted wire or 0.8 mm dia. solid wire				
Usable wires and Twisted wire		0.3 mm^2	0.5 mm ²	0.75 mm^2	1.25 mm ²	
tensile strength	Solid wire	0.5 mm dia.	0.8 mm dia.	1.0 mm dia.		
	Tensile strength	10 N	20 N	30 N	40 N	
Length of exposed wire		10 ±1 mm				



22 mm pushbutton switch

A22 comes in a wide variety of shapes and colours and is installable in 22-dia. or 25-dia. panel cutouts. The switch unit can easily be mounted. A22 is mounted using either open-type (fork-type) or closed-type (round-type) crimp terminals.

- Finger-protection mechanism on switch unit provided as standard feature
- Increased wiring efficiency with three-row mounting of switch blocks
- IP65 oil-resistant (non-lighted models), IP65 (lighted models)
- Lighted and non-lighted, flat, projection and half- and full-guard versions
- EN60947-5-1, UL and cUL approved

Ordering information

Pushbutton									
Illumination	Colour	Order code							
		Flat type	Projection type	Full-guard type	Half-guard type	Square/ projection type	Square/ full-guard type	Round/ mushroom type (30-dia. head)	Round/ mushroom type (40-dia. head)
Non-lighted	Red	A22-FR	A22-TR	A22-GR	A22-HR	A22-CR	A22-DR	A22-SR	A22-MR
	Green	A22-FG	A22-TG	A22-TG	A22-HG	A22-CG	A22-DG	A22-SG	A22-MG
	Yellow	A22-FY	A22-TY	A22-GY	A22-HY	A22-CY	A22-DY	A22-SY	A22-MY
	White	A22-FW	A22-TW	A22-GW	A22-HW	A22-CW	A22-DW	A22-SW	A22-MW
	Blue	A22-FA	A22-TA	A22-GA	A22-HA	A22-CA	A22-DA	A22-SA	A22-MA
	Black	A22-FB	A22-TB	A22-GB	A22-HB	A22-CB	A22-DB	A22-SB	A22-MB
Lighted	Red	_	A22L-TR	A22L-GR	A22L-HR	A22L-CR	A22L-DR	_	_
	Green	_	A22L-TG	A22L-GG	A22L-HG	A22L-CG	A22L-DG	_	_
	Yellow	_	A22L-TY	A22L-GY	A22L-HY	A22L-CY	A22L-DY	_	_
	White	-	A22L-TW	A22L-GW	A22L-HW	A22L-CW	A22L-DW	-	_
	Blue	-	A22L-TA	A22L-GA	A22L-HA	A22L-CA	A22L-DA	-	_
Buttonsize in r	nm	29.7 dia. x 12D	29.7 dia. x 19D	29.7 dia. x 19D	29.7 dia. x 12/18.5D	29.8 mm ² x 18D	29.8 mm ² x 18D	30 dia. x 32D	40 dia. x 32D

c.,	.:4	~1	•	_
ЭV	VΙΤ	CI	11:	

	Switch	Contacts	Oder code					
	operation		Non- lighted models	Lighted models				
			Without vol		With voltage red	luction unit		
			reduction u	nit	110 VAC	220 VAC		
	Momentary	SPST-NO	A22-10M	A22L-10M	A22L-10M-T1	A22L-10M-T2		
		SPST-NC	A22-01M	A22L-01M	A22L-01M-T1	A22L-01M-T2		
		SPST-NO + SPST-NC	A22-11M	A22L-11M	A22L-11M-T1	A22L-11M-T2		
		DPST-NO	A22-20M	A22L-20M	A22L-20M-T1	A22L-20M-T2		
		DPST-NC	A22-02M	A22L-02M	A22L-02M-T1	A22L-02M-T2		
	Alternate	SPST-NO	A22-10A	A22L-10A	A22L-10A-T1	A22L-10A-T2		
		SPST-NC	A22-01A	A22L-01A	A22L-01A-T1	A22L-01A-T2		
		SPST-NO + SPST-NC	A22-11A	A22L-11A	A22L-11A-T1	A22L-11A-T2		
		DPST-NO	A22-20A	A22L-20A	A22L-20A-T1	A22L-20A-T2		
		DPST-NC	A22-02A	A22L-02A	A22L-02A-T1	A22L-02A-T2		

Switch blocks

	Standard load	Order code
Switch blocks	SPST-NO	A22-10
	SPST-NC	A22-01
	DPST-NO	A22-20
4	DPST-NC	A22-02

Lamp – LED

AC/DC	LED light	Order code					
		Operating voltage					
		6 V	12 V	24 V	24 V superbright		
DC	Red	A22-6DR	_	_	_		
	Green	A22-6DG	_	_	_		
	Yellow *1	A22-6DY	_	_	_		
	Blue	A22-6DA	_	_	_		
AC	Red	A22-6AR	_	_	_		
	Green	A22-6AG	_	_	_		
	Yellow *1	A22-6AY	_	_	_		
	Blue	A22-6AA	_	_	_		
AC and DC	Red	_	A22-12AR	A22-24AR	A22-24ASR		
	Green	_	A22-12AG	A22-24AG	A22-24ASG		
	Yellow *1	_	A22-12AY	A22-24AY	A22-24ASY		
	Blue	_	A22-12AA	A22-24AA	A22-24ASA		

 $^{^{\}star1}$ Used when the pushbutton colour is yellow or white

Lamp - incandescent lamp

Order code		
Operating voltage		
5 VAC/VDC	12 VAC/VDC	24 VAC/VDC
A22-5	A22-12	A22-24



Accessories

Item				Remarks	Order code
Lamp sockets	Direct lighting			Used when changing the lighting method (LED only)	A22-TN
	Voltage-reduction	Voltage-reduction lighting 220 VAC			A22-T2
Mounting latches			Order mounting latches only when mounting switch blocks or lamp sockets are purchased individually	A22-3200	
Legend plate	Large size	With snap-in legend plate, without text, black		Snap-in legend plate is acrylic	A22Z-3333
frames		Without snap-in legend plate			A22Z-3330
Sealing caps	For projection models		Used to prevent dust or water from entering the operation unit (pushbutton, etc.), colour: Opaque, material: Silicon	A22Z-3600T	
Three-throw spacer		Used when mounting three non-lighted switches	A22Z-3003		
Control boxes			One hole	material, Delugarhenata regin	A22Z-B101
(enclosures)			Two holes		A22Z-B102
			Three holes		A22Z-B103
Snap-in legend	Standard size	Without text	White	material: Acrylic	A22Z-3443W
plates			Transparent		A22Z-3443C
		White text on black background	ON		A22Z-3443B-5
			0FF		A22Z-3443B-6
			DOWN		A22Z-3443B-8
			POWER ON		A22Z-3443B-9
	Large size	Without text	White	Attached to the large-size legend plate frame,	A22Z-3453W
			Transparent	material: Acrylic	A22Z-3453C
	For emergency	60-dia. round plate with black letters on a yellow background		"EMERGENCY STOP" is engraved on the plate.	A22Z-3466-1
	stop switch 90-dia. round plate with black letters on a yellow background		Used as an emergency stop switch legend plate	A22Z-3476-1	
Lamp extractor				Rubber tool used to easily replace lamps	A22Z-3901
Tightening wren	ch			Tool used to tighten nuts from the back of the panel	A22Z-3905

Specifications

Recognized organization	Standards	File number
UL, cUL	UL508	E41515
– EN60947-5-1 –		
Contact vatings (standard load)		

Contact ratings (standard load)

Rated carry	Rated voltage	Rated current (A)				
current (A)		AC15 (inductive load)	AC12 (resistive load)	DC13 (inductive load)	DC12 (resistive load)	
10	24 VAC	10	10	_	_	
	110 VAC	5	10	_	_	
	220 VAC	3	6	_	_	
	380 VAC	2	3	_	_	
	440 VAC	1	2	_	_	
	24 VDC	_	_	1,5	10	
	110 VDC	_	_	0,5	2	
	220 VDC	_	_	0,2	0,6	
	380 VDC	-	_	0,1	0,2	

Contacts (microload)

Rated applicable load	Minimum applicable load
50 mA at 5 VDC (resistive load)	1 mA at 5 VDC

|--|

Rated voltage	Rated current	Operating voltage
6 VDC	60 mA (20 mA)	6 VDC ±5%
6 VAC	60 mA (20 mA)	6 VAC/VDC ±5%
12 VAC/VDC	30 mA (10 mA)	12 VAC/VDC ±5%
24 VAC/VDC	15 mA (10 mA)	24 VAC/VDC ±5%

Super-bright LED indicator

Rated voltage	Rated current	Operating voltage
24 VAC/VDC	15 mA	24 VAC/VDC ±5%

Incandescent lamp

Rate	d voltage	Rated current	Operating voltage
6 VA	C/VDC	200 mA	5 VAC/VDC
14 V	AC/VDC	80 mA	12 VAC/VDC
28 V	AC/VDC	40 mA	24 VAC/VDC
130	VAC/VDC	20 mA	100 VAC/VDC

Voltage-reduction lighting

Rated voltage	Operating voltage	Applicable lamp (BA8S/13_ gold)
110 VAC	95 to 115 VAC	LED Lamp (A22-24A_)
220 VAC	190 to 230 VAC	

		Pushbutton s	witches	Emergency s	top switches	Knob-type selector switches	;	Key-type selector switch
		Non-lighted	Lighted	Non-lighted	Lighted	Non-lighted	Lighted	Non-lighted
Allowable operating	Mechanical	Momentary op 60 operations		30 operations	/minute max.	Manual release: 30 operations automatic release: 30 operation		
frequency	Electrical	30 operations/	30 operations/minute max.			30 operations/minute max.		
Durability (number of	Mechanical	Momentary op 5,000,000	eration:	Momentary op	peration: 300,000	500,000	100,000	500,000
operations min.)	· Liccuitai	500,000 300,000		500,000	100,000	500,000		
Ambient	Operating	-20 to 70°C	-20 to 55°C	-20 to 70°C	-20 to 55°C	-20 to 70°C	-20 to 55°C	-20 to 70°C
temperature	Storage	-40 to 70°C	-40 to 70°C	-40 to 70°C	-40 to 70°C	-40 to 70°C	-40 to 70°C	-40 to 70°C
Degree of prot	ection	IP65 (oil-resistant)	IP65	IP65 (oil-resistant)	IP65	IP65 (oil-resistant)	IP65	IP65 (oil-resistant)
Size in mm (in-panel only)		34Hx34Wx54.	7D, 34Hx34Wx	72.7D for DPST	switches			





Emergency stop switch

The A165E line-up offers E-Stop switches with various head types. For flexible application, a wide range of accessories is provided. To set up easy installation and maintenance, various contact combinations are available.

- Direct opening mechanism with minimum contact separation of 3 mm
- Safety lock mechanism prevents misuse
- Short mounting depth
- · Modular construction; easy installation using snap-in switch

Ordering information

Switches	Rated voltage	Pushbutton color	Pushbutton size	Terminal	Contact	Order code Standard load		
						(125 VAC at 5 A, 250 VAC at 3 A, 30 VDC at 3 A)		
LED	24 VDC	Red	Red 30 dia.	30 dia.	Solder terminal	SPST-NC	A165E-LS-24D-01	
					DPST-NC	A165E-LS-24D-02		
None	-	40 dia.		SPST-NC	A165E-S-01			
					DPST-NC	A165E-S-02		
					TPST-NC	A165E-S-03U		
LED	24 VDC			4	40 dia.	40 dia.	SPST-NC	A165E-LM-24D-01
							DPST-NC	A165E-LM-24D-02
None	-			SPST-NC	A165E-M-01			
				DPST-NC	A165E-M-02			
							TPST-NC	A165E-M-03U

Note: The above models have a surface indication of "RESET." Models with "STOP" indication are also available. For further information, contact your Omron representative.

Accessories (order separately)

docosonios (oraci soparatory)					
Item	Туре	Precautions	Order code		
Yellow plate	Yellow, 45 dia.	Use this as an emergency stop nameplate.	A16Z-5070		
Panel plug	Round	Used for covering the panel cutouts for future panel expansion.	A16ZT-3003		
Tightening tool	-	Useful for repetitive mounting. Be careful not to tighten excessively.	A16Z-3004		
Extractor	-	Convenient for extracting the switch and lamp.	A16Z-5080		

Rated voltage	Resistive load		
	A165E series	A165EU series	
125 VAC	5 A	1 A	
250 VAC	3 A	0.5 A	
30 VDC	3 A	1 A	
Minimum applicable load	150 mA at 5 VDC	1 mA at 5 VDC	

Features	Characteristics
Operating force (OF) max.	14.7 N
Releasing force (RF) min.	0.1 N·m
Pretravel (PT)	3.5±0.5 mm (3±0.5 mm In case of A165E_U series)

Item		Emergency stop switch		
Allowable operating frequency	Mechanical	20 operations/minute max.		
	Electrical	10 operations/minute max.		
Insulation resistance		100 M Ω min. (at 500 VDC)		
Dielectric strength		1,000 VAC, 50/60 Hz for 1 min between terminals of same polarity 2,000 VAC, 50/60 Hz for 1 min between terminals of different polarity and also between each terminal and ground 1,000 VAC, 50/60 Hz for 1 min between lamp terminals *1		
Durability	Mechanical	100,000 operations min.		
	Electrical	100,000 operations min.		
Ambient temperature		Operating: -10 to 55°C (with no icing or condensation) Storage: -25 to 65°C (with no icing or condensation)		
Protection against electric shock		Class II		

^{*1} LED not mounted. Test them with the LED removed.





Emergency stop switch

The A22E line-up of E-Stop switches offers various head types as well as lighted models. E-stop shrouds and control boxes as accessories provide flexibility in appli-

- Direct opening mechanism with minimum contact separation of 3 mm
- · Safety lock mechanism prevents misuse
- · Easy mounting of switch block
- · Lighted models for easy diagnosis and maintenance
- · Modular design for flexibility in application

Ordering Information

Non-lighted models

Description	Output	Color of cap	Order code
30-dia. head	SPST-NC	Red	A22E-S-01
Push-lock	SPST-NO/SPST-NC		A22E-S-11
Turn-reset	DPST-NC		A22E-S-02
40-dia. head	SPST-NC		A22E-M-01
Push-lock	SPST-NO/SPST-NC		A22E-M-11
Turn-reset	DPST-NC	Red	A22E-M-02
60-dia. head	SPST-NC		A22E-L-01
Push-lock	SPST-NO/SPST-NC		A22E-L-11
Turn-reset	DPST-NC		A22E-L-02
30-dia. head	SPST-NC		A22E-SK-01
Push-lock	SPST-NO/SPST-NC		A22E-SK-11
Key-reset	DPST-NC		A22E-SK-02
40-dia. head	SPST-NC		A22E-MK-01
Push-lock	SPST-NO/SPST-NC		A22E-MK-11
Key-reset	DPST-NC		A22E-MK-02

Lighted models

Description	Output	Lighting	Rated voltage	Color of cap	Order code
40-dia. head	SPST-NC		24 VAC/VDC		A22EL-M-24A-01
Push-lock	SPST-NO/SPST-NC		24 VAC/VDC		A22EL-M-24A-11
Turn-reset	DPST-NC		24 VAC/VDC		A22EL-M-24A-02
40-dia. head	SPST-NC		220 VAC		A22EL-M-T2-01
Push-lock	SPST-NO/SPST-NC		220 VAC		A22EL-M-T2-11
Turn-reset	DPST-NC		220 VAC		A22EL-M-T2-02

Accessories (Order separately)

Item	Classification	Remarks	Order code
Control boxes (enclosures)	One hole	Material: Polycarbonate resin	A22Z-B101
	One hole, yellow box (for emergency stop)		A22Z-B101Y
	Two holes		A22Z-B102
	Three holes		A22Z-B103
Legend plates for	60-dia. black letters on yellow back-ground	"EMERGENCY STOP" is indicated on the plate.	A22Z-3466-1
emergency stop	90-dia. black letters on yellow back-ground		A22Z-3476-1

Specifications

Contacts (standard load)

· · · · · · · · · · · · · · · · · · ·						
	Rated carry	Rated voltage	Rated current (A)			
current		AC15	AC12	DC13	DC12	
10	24 VAC	10	10			
	220 VAC	3	6			
	24 VDC			1.5	10	
	220 VDC			0.2	0.6	

- 1. Rated current values are determined according to the testing conditions. The above ratings were obtained by conducting tests under the following conditions.

 (1) Ambient temperature: 20×±2°C

 (2) Ambient humidity: 65±5%

 (3) Operating frequency: 20 operations/minute

 - 2. Minimum applicable load: 10 mA at 5 VDC

Contacts (microload)

Rated applicable load	Minimum applicable load			
50 mA at 5 VDC (resistive load)	1 mA at 5 VDC			

Characteristics

Item		Emergency stop switches		
		Non-lighted model: A22E	Lighted model: A22EL	
Dielectric strength		2,500 VAC, 50/60 Hz for 1 min between terminals of same polarity 2,500 VAC, 50/60 Hz for 1 min between terminals of different polarity and also between each terminal and ground		
Durability	Mechanical	Momentary operation: 300,000 operations min.		
Electrical		300,000 operations min.		
Degree of protection		IP65 (oil-resistant)		



ER-series



Emergency stop switch

- Tension indicator the tension indicator makes the system easy to set up and to maintain the proper rope tension
- Heavy-duty housing the die-cast housing and stainless steel eye nut makes the ER series rope pull switches suitable for demanding industrial applications
- Vibration tolerant the snap-acting switch contacts protect against nuisance tripping due to vibration
- Integral E-stop the E-stop button provides emergency stopping capability at the extreme end of the installation and is field serviceable
- ER6022 available in stainless steel housing
- ER6022, ER1022 and ER1032 available in explosion proof housing

Ordering information

Standard models

Aluminium die-cast housing

E-Stop	Indicator beacon	Contacts	Wiring entry	Order code
Not included	-	2 N/C + 1 N/O	3 x M20	ER5018-021M
Not included	-	3 N/C	3 x M20	ER5018-030M
Included	-	2 N/C + 1 N/O	3 x M20	ER5018-021ME
Included	-	3 N/C	3 x M20	ER5018-030ME
Not included	Not included	2 N/C + 1 N/O	3 x M20	ER6022-021M
Not included	Not included	3 N/C	3 x M20	ER6022-030M
Not included	Included (24 VDC)	2 N/C + 1 N/O	3 x M20	ER6022-021ML
Not included	Included (24 VDC)	3 N/C	3 x M20	ER6022-030ML
Included	Not included	2 N/C + 1 N/O	3 x M20	ER6022-021ME
Included	Not included	3 N/C	3 x M20	ER6022-030ME
Included	Included (24 VDC)	2 N/C + 1 N/O	3 x M20	ER6022-021MEL
Included	Included (24 VDC)	3 N/C	3 x M20	ER6022-030MEL
Included	Included (24 VDC)	4 N/C + 2 N/O	4 x M20	ER1022-042MELL
Included	Included (24 VDC)	4 N/C + 2 N/O	4 x M20	ER1022-042MELR
Included	Included (24 VDC)	4 N/C + 2 N/O	4 x M20	ER1032-042MEL

Stainless steel housing

E-Stop	Indicator beacon	Contacts	Wiring entry	Order code
Not included	Not included	2 N/C + 2 N/O	3 x M20	ER6022-022MSS
Not included	Not included	3 N/C + 1 N/O	3 x M20	ER6022-031MSS
Not included	Included	2 N/C + 2 N/O	3 x M20	ER6022-022MLSS
Not included	Included	3 N/C + 1 N/O	3 x M20	ER6022-031MLSS
Included	Not included	2 N/C + 2 N/O	3 x M20	ER6022-022MESS
Included	Not included	3 N/C + 1 N/O	3 x M20	ER6022-031MESS
Included	Included	2 N/C + 2 N/O	3 x M20	ER6022-022MELSS
Included	Included	3 N/C + 1 N/O	3 x M20	ER6022-031MELSS

Explosion proof models

Aluminum die-cast housing

E-Stop	Indicator beacon	Contacts	Wiring entry	Order code	
Not included	Not included	1 N/C + 1 N/O	pre-wired, 3 m	XER6022-011C3	
Not included	Not included	1 N/C + 1 N/O	pre-wired, 3 m	XER1022-011C3L	
Not included	Not included	1 N/C + 1 N/O	pre-wired, 3 m	XER1022-011C3R	
Not included	Not included	1 N/C + 1 N/O	pre-wired, 3 m	XER1032-011C3	
Stainless steel housing					

E-Stop	Indicator beacon	Contacts	Wiring entry	Order code
Not included	Not included	1 N/C + 1 N/O	pre-wired, 3 m	XER6022-011C3SS
Not included	Not included	2 N/C	pre-wired, 3 m	XER6022-020C3SS



Accessories

ER-series

Item	Applicable model	Order code
Replacement Lid	ER 5018	SM06-SL400
	ER 6022	SM06-SL500
	ER6022-SS stainless steel	SM06-SLXER6022SS
Replacement Lid/LED, 24 VDC	ER 1022	EM06-SL710
	ER 1032	SM06-SL711
	ER6022-SS stainless steel	SM06-SLXER622LSS
Replacement Lid/LED	ER 6022	SM06-SL510
Rope kit, 5 m, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	RK5
Rope kit, 10 m, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	RK10
Rope kit, 20 m, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	RK20
Rope kit, 50 m, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	RK50
Rope kit, 80 m, stainless steel	ER 6022, ER1022, ER1032	RK80
Rope only, 5 m	ER 5018, ER 6022, ER 1022, ER 1032	R5M
Rope only, 10 m	ER 5018, ER 6022, ER 1022, ER 1032	R10M
Rope only, 20 m	ER 5018, ER 6022, ER 1022, ER 1032	R20M
Rope only, 50 m	ER 5018, ER 6022, ER 1022, ER 1032	R50M
Rope only, 100 m	ER 5018, ER 6022, ER 1022, ER 1032	R100M
Rope only, 126 m	ER 5018, ER 6022, ER 1022, ER 1032	R126M
Tensioner gripper, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	SM06-TG00
Eye bolt stainless steel, 8 per pack	ER 5018, ER 6022, ER 1022, ER 1032	SM06-EB10
Double loop clip, stainless steel, 4 per pack	ER 5018, ER 6022, ER 1022, ER 1032	SM06-DL20
Thimble stainless steel, 4 per pack	ER 5018, ER 6022, ER 1022, ER 1032	SM06-THSS
Turnbuckle, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	SM06-TB30
Spring, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	SM06-SP50
Rope pulley, stainless steel	ER 5018, ER 6022, ER 1022, ER 1032	SM06-RPSS
E-Stop mechanism	ER 5018, ER 6022, ER 1022, ER 1032	SM06-ES60

Specifications

Standard models

Item		Applicable model				
		ER 5018	ER 6022	ER 1022	ER 1032	
	Contact configurations	2 N/C + 1 N/O, 3 N/C	2 N/C + 1 N/O, 3 N/C, 3N/C + 1N/O	4 N/C + 2 N/O	4 N/C + 2 N/O	
	Safety contacts	2 N/C, 3 N/C	2 N/C, 3 N/C	4 N/C		
Electrical	Switching ability	AC: 120 V-6 A, 240 V-3 A, inductive DC: 24 V-2.5 A, inductive				
lect	Auxiliary contacts	1 N/O		2 N/0		
ш	Max. switching current/Volt/Amp	240 V/720 VA				
	Electrical life	1,000,000 minimum				
	LED indicator beacon	_	24 VDC			
	Max. rope span	40 m	80 m	125 m	125 m each side	
ical	Case material	Die-cast aluminum alloy				
Mechanical	Eye nut material	Stainless steel				
Mec	Wiring entry	3 x M20		4 x M20		
	Mechanical life	1,000,000 minimum				
ᆿ늘	Protection	IP67 (NEMA 6)				
Environ- mental	Operating temperature	-25 to 80°C				
급 =	Cleaning	Water washdown				
Com- pliance	Standards	IEC947-5-1, IEC947-5-5, EN418, ULS	EC947-5-1, IEC947-5-5, EN418, UL508, BS5304			
Com- pliance	Approvals/listings	CE marked for all applicable directive	es, UL and C-UL			

Explosion proof models

Item	Item		Applicable model			
			XER6022	XER1022	XER1032	
	Contact configurat	ion	1 N/C + 1 N/O, 2 N/C			
	Safety contact		1 N/C, 2 N/C			
	Auxiliary contact		1 N/O			
	Rated voltage AC1	5	400 VAC	250 VAC	250 VDC	
cal	Rated current		2 A AC	4 A AC	0.15 A DC	
Electrical	AC ratings	Voltage	250 V	125 V		
ä		Resistive load	5A			
		Inductive load	3A			
	Switching ability	Voltage	250V	30V		
	DC ratings	Resistive load	0,4A	7A		
		Inductive load	0,03A	5A		
Com- pliance	Ex-classification		II 2 G	EEx d II C T6		
S e la	Certification		PTB 00 ATEX 1093X	IBExU 01 ATEX 1007X		



ER-series


Accessories

RK rope tension kit




The RK rope tension kit comes with all of the required hardware for most installations. A spring is required as shown in the installation example below.

Installation Hardware



Individual hardware items may be purchased for specific installation requirements.



Nomenclatur/how to order:

$\underline{MP}_{1} - \underbrace{502}_{2} - \underbrace{RYGBC - B0438}_{5}$

1. MP: Standard body MPS: Short body

- 2. Stack
- 3. Rated voltage 02: 24 V AC/DC
- 4. Color of LED R: Red
 - Y: Yellow G: Green B: Blue

5. Color of lense

Blank: Colored lens

B0438: Clear lens

C: Clear/White Top to bottom

Super slim 30 mm silver body signal tower ideal for small devices

MP/MPS signal towers provide double insulation and superior UV resistant and light translucent AS resin lenses for enhanced durability and reliability in application environment. The 30mm diameter is ideal for small and mid-sized machines.

Up to 5 colored modules can be combined using a single mounting hole. Modules can be easily added without dismounting the whole signal tower to reduce installation effort.


- Special pre-wired versatile with 1 m connection cable
- NPN/ PNP compactible
- IP65
- Each color of LED module corresponds to the lead wire color.
- · Available colors are Red, Yellow, Green, Blue and Clear/White.

Ordering information

Number of stacks	Rated voltage	Power consumption	Open collector	Order code
1	24 VAC/VDC	0.7 W	NPN/PNP	MP/MPS-102
2		1.4 W		MP/MPS-202
3		2.0 W		MP/MPS-302
4		2.6 W		MP/MPS-402
5		3.2 W		MP/MPS-502

Features

Patented reflection system increases visibility.







Good visibility from any direction


Interchangeable LED modules

Changeable color sequence: Easy to add/remove up to 5 colored modules even after installation.
 Note: LED modules of the same color will light up simultaneously.


The wiring remains the same.

Each color of LED module corresponds to the

Dimensions




Wiring diagram



MP/MPS

Size	30 mm diameter
Size	30 min diameter
Input voltage options	24 VAC/VDC
Functions available	Continuous only
Mounting options	Direct mount only: includes M22 mounting nut and sealing gasket
Body style	pre-assembled, pre-wired Interchangeable and stackable after purchase
Body color	Silver
Tiers	1-5 modules can be stacked
Module colors	Red / Yellow / Green / Blue / Clear-White (for sunlight applications: clear-lense modules in all colors available)
Alarms (FB style only)	 CE UL component recognition (US) UL component recognition (Canada) RoHS
Protection	IP-65
Control options	 Dry contact closure such as switches or relay contacts Open-collector transistor (NPN or PNP) for 24 VDC Direct voltage control





Versatile, cost and energy efficient LED signal tower for every need

The LME series provides the latest in LED technology. 1 to 5 modules can be arranged in tiers. The original dual reflection system for enhanced light diffusion, creates bright distinctive illumination while saving energy (patent pending).

Available Colors are Red, Yellow, Green, Blue and Clear/White.

All colors as clear-lense modules available

- Diameter: 60 mm
- 2 selectable built- in alarms with adjustable volume up to 90 dB at 1 m for FB type
- Special pre-wired versatile and flexible cable connection of 3 m
- UV resistant and light translucent AS resin lenses
- NPN/ PNP compatible
- IP 65

Nomenclature/how to order

1. Stack

1 ~ 5

2. Rated voltage 02: 24V AC/DC

3. Body color

Blank: Ivory white

N: Black color

4. Type

Blank: Continuous light

FB: Continuous light or flashing light with audible alarm

audibie

5. Mount

Blank: Pole mount

K: Pole mount (with SZ-020)

W: Direct mount

6. Color of LED

R: Red Y: Yellow

G: Green

B: Blue

C: Clear/White

7. Color of Lens
Blank: Colored lens
Z: Clear lens

Ordering information

Number of stacks	Mount	Model	Rated voltage	Power	Open collector	Order code			
				consumption		Continuos light	Continuous light with audible alarm		
1	Pole mount	LME-102	24 VAC/DC	2.2 W	NPN/ PNP	LME-102-C	LME-102-FB-C		
	Direct mount		24 VAC/DC			LME-102W-C	LME-102-FBW-C		
2	Pole mount	LME-202	24 VAC/DC	3.4 W	3.4 W	3.4 W		LME-202-C	LME-202-FB-C
	Direct mount		24 VAC/DC			LME-202W-C	LME-202-FBW-C		
3	Pole mount	LME-302	24 VAC/DC	3.8 W		LME-302-C	LME-302-FB-C		
	Direct mount		24 VAC/DC			LME-302W-C	LME-302-FBW-C		
4	Pole mount	LME-402	24 VAC/DC	4.2 W		LME-402-C	LME-402-FB-C		
	Direct mount		24 VAC/DC			LME-402W-C	LME-402-FBW-C		
5	Pole mount	LME-502	24 VAC/DC	4.6 W		LME-502-C	LME-502-FB-C		
	Direct mount 24 VAC/DC			LME-502W-C	LME-502-FBW-C				


Optional parts

Тур	Material	Order code
Wall mount bracket	Aluminum alloy die-cast	SZ-017
	ABS resin	SZ-020
	PBT/ ABS resin	SZ-028
Mount bracket	Aluminum alloy die-cast	SZ-016A
	Aluminum alloy die-cast	SZ-010

Тур	Height	Material	Order code
Pole	100 mm	Aluminium	Pole-100A21
		Steel	Pole-100S21
	300 mm	Aluminium	Pole-300A21
		Steel	Pole-300S21
	800 mm	Aluminium	Pole-800A21
		Steel	Pole-800S21




Dimensions



Wiring diagram

LME(-W)/LME(-W)-S·Q/LMS [Continuous type]



Features

Interchangeable LED modules

- Changeable color sequence: Easy to add / remove up to 5 colored modules even after installation.
- · Note: LED modules of the same color within a signal tower will light up simultaneously.

The wiring remains the same

Each color of LED module corresponds to the lead wire color.



Easy to add and remove

If the number of LED module is changed, center shaft must be purchased.

Dual reflection system




PATLITE's original dual reflection system with its exclusive hybrid prism-cut lens and 5 color LED modules create bright, distinctive, even illumination.



To bring more attention to certain conditions, two, User-selectable, Alarms integrated in the Base module with adjustable volume up to 85 dB at 1m are available.

Size	60 mm diameter
Input voltage options	• 24 VAC/VDC
Functions available	Continuous only Continuous, flashing, alarms
Mounting options	Pole mount: with 300 mm aluminum pole, plastic circular bracket Direct mount: includes 3 mounting nuts
Body style	Pre-assembled, pre-wired Interchangeable and stackable after purchase
Body color	Beige (optional: Black or silver)
Tiers	1-5 modules can be stacked
Module colors	Red / Yellow / Green / Blue / Clear/White (for sunlight applications: clear-lense modules in all colors available)
Alarms (FB style only)	 Alarm 1: selectable, single-tone, intermittent (fast beep) alarm, 85 dB (at 1 m) Alarm 2: selectable, single tone, intermittent (slow beep) alarm, 85 dB (at 1 m)
Ratings	 CE UL component recognition (US) UL component recognition (Canada) RoHS
Protection	 IP-65 (LME, LME-W) IP-54 (LME-FB, LME-FBW) Type 4/4X/13 (indoor, direct-mount only)
Control options	 Dry contact closure such as switches or relay contacts Open-collector transistor (NPN or PNP for 24 VDC) Direct voltage control for 24 VDC, continuous and alarm functions only





Versatile modular signal tower featuring easy assembly and wiring designed for every need.

LU5 Series - Medium size modular system provides beside hybrid prism cut lens for enhanced visibility from any direction and distance two selectable sound patterns up $% \left(1\right) =\left(1\right) \left(1\right) \left($ to 85 dB. Main features are the interchangeable LED modules and the color coordinated wiring for easy alignment.

- · Diameter: 50 mm
- Base modules available in ivory white or in silver
- . Up to 5 LED modules can be used on the light tower
- Modules of the same color operate from different terminals
- Two, user selectable, alarms integrated in the base module with adjustable volume up to 85 dB at 1 m

Nomenclature/how to order

LED module

LU5-E-R

- 1. E: LED unit
- 2. Color of LED

 - Y: Yellow
 - G: Green
 - B: Blue
 - Clear/White C:

Base module

LU5-02UFB

1. Rated voltage 02: 24 VDC

2. Unit color Blank: Ivory white Silver color

3. Type

Blank: Continuous light

FB: Continuous or flashing light with audible alarm

Ordering information

LED module

Module color	Power consumption	Rated voltage	Operation voltage	Operation temperature range	Mass	Order code
Red	52 mA/1.25 W	24 VDC	Rated voltage ±10% (21.6~26.4 V)	-30°C~+60°C	44 g ±10%	LU5-E-R
Yellow						LU5-E-Y
Green	42 mA/1.0 W					LU5-E-G
Blue						LU5-E-B
Clear						LU5-E-C

Base module

Тур	Alarm/Flash	Power consumption	Rated voltage	Operation voltage	Operation temperature range	Mass	Open collector	Order code
Standard body	Continuous	1.2 W	24 VDC	Rated voltage ±10%	-30°C~+60°C	182g ±10%	PNP/ NPN	LU5-02*
	2 Sounds/Flashlight			(21.6 ~ 26.4 V)		200g ±10%		LU5-02FB*

^{*} Ivory white: black, silver: add "U"

Optional parts

Тур	Material	Order code
Wall mount bracket	Aluminum alloy die-cast	SZ-017
	ABS resin	SZ-020
Upper bracket	Metal	SZ-60NPT
		SZ-60U
Mount bracket	Aluminum alloy die-cast	SZ-016A
		SZ-70B

Тур	Height	Material	Order code
Pole	100 mm	Aluminium	Pole-100A21
	300 mm	Aluminium	Pole-300A21
	800 mm	Aluminium	Pole-800A21

Features




LED module is stackable and reconfigurable even after installation


IP 65: Implemented o rings seal out liquids so that the tower can be used in wet conditions.




Dimensions



Wiring diagram




How to order



Size	50 mm diameter
Input voltage options	24 VDC
Functions available	Continuous only Continuous, flashing, alarms
Mounting options	Direct mount only, includes 3 mounting nuts
Body styles	Component style, wiring terminals provided Interchangeable and stackable after purchase
Body colours	Beige
Tiers	1-5 modules can be stacked
Module colors	Red / Yellow / Green / Blue / Clear
Alarms (FB style only)	 Alarm 1: selectable, single-tone, continuous alarm, 85 dB (at 1 m) Alarm 2: selectable, single tone, intermittent (slow beep) alarm, 85 dB (at 1 m)
Ratings	CE UL listed (US) UL listed (Canada) RoHS
Protection	 IP-65 Type 4 / 4X / 13 (indoor only)
Control options	 Dry contact closure such as switches or relay contacts Open-collector transistor (NPN or PNP) for 24 VDC Direct voltage control for 24 VDC, continuous and alarm functions only









Versatile modular signal tower featuring easy assembly and wiring designed for every need.

LU7 presents ultra bright LEDs combined with an innovative prism lens design. 1 to 5 modules can be arranged in tiers.

- Diameter: 70 mm
- . Base module in 2 sizes and 3 colors
- Different modules: standard LED, strobe LED and sound
- Two, user selectable, alarms integrated in the base module with adjustable volume up to 90 dB at 1 m.
- · Color-coordinated and spring-loaded terminal block

Ordering information

LED module

Тур	Module color	Power consumption	Rated voltage	Operation voltage	Operation temperature range	Mass	Order code
Standard	Red	52 mA/1.25 W		Rated voltage ±10% (21.6~26.4 V)	-30°C~+60°C	60 g ±10%	LU7-E-R
G B	Yellow						LU7-E-Y
	Green	42 mA/1.0 W					LU7-E-G
	Blue						LU7-E-B
	Clear/White						LU7-E-C
Strobe	Red	290 mA 140 mA 270 mA		Rated voltage ±10% (21.6~26.4 V)	-30°C~+60°C	0,07 kg	LU7-XE-R
	Yellow						LU7-XE-Y
	Green						LU7-XE-G
	Blue						LU7-XE-B
	Clear/White	280 mA					LU7-XE-C

Base module

Тур	Alarm/Flash	Power consumption	Rated voltage	Operation voltage	Operation temperature range	Mass	Open collector	Order code
Short body	Continuous	1.2 W	24 VDC	Rated voltage \pm 10%	-30°C~+60°C	150 g ±10%	PNP/ NPN	LU7-02S*
Standard body	Continuous		(21.6~26.4 V)	(21.6~26.4 V)		250 g ±10%	6	LU7 - 02*
	2 Sounds/Flashlight					280 g ±10%		LU7 -02FB*

^{*} Ivory white: blank, black: add "K", silver: add "U"

Optional parts

Тур	Material	Order code
Wall mount bracket	Aluminum alloy die-cast	SZ-017
	PBT/ ABS resin	SZ-018
		SZ-018U
		SZ-018K
	ABS resin	SZ-020
Upper bracket	Metal	SZ - 50U
		SZ - 50UU
		SZ - 50KU
		SZ - 50NPT
Mount bracket	Aluminum alloy die-cast	SZ-016A
		SZ-70B

Тур	Height	Material	Order code
Pole	100 mm	Aluminium	Pole-100A21
		Steel	Pole-100S21
	300 mm	Aluminium	Pole-300A21
		Steel	Pole-300S21
	800 mm	Aluminium	Pole-800A21
		Steel	Pole-800S21
		Pole 100 mm 300 mm 800 mm	Pole 100 mm Aluminium Steel 300 mm Aluminium Steel Steel

Voice and sound module (unique sound module in all directions)


Rated voltage	Power consumption	Mass	Order code
24 VDC	3.5 W	0.17 kg	LU7-V1


Features

Easy alignment:


Color-coordinated terminal block: Corresponds to the lens colors for quick wiring verification in the base unit.








How to order







Size	70 mm diameter
Input voltage options	• 24 VDC
Functions available	 Continuous only Continuous, flashing, alarms
Mounting options	Direct mount only: includes three mounting nuts
Body style	Component style, wiring terminals provided Interchangeable and stackable after purchase
Body color	BeigeBlackSilver
Tiers	1-5 modules can be stacked
Module colors	Red / Yellow / Green / Blue / Clear Standard LED modules Strobe-flash LED modules (24 V bases only)
Alarms (FB style only)	 Alarm 1: selectable, single-tone, continuous alarm, 90 dB (at 1 m) Alarm 2: selectable, single tone, intermittent (slow beep) alarm, 90 dB (at 1 m)
Ratings	CE UL listed (US) UL listed (Canada) RoHS
Protections	IP-65 Type 4/4X/13 (indoor only)
Control options	 Dry contact closure such as switches or relay contacts Open-collector transistor (NPN or PNP for 24 VDC Direct voltage control for 24 VDC, continuous and alarm functions only




PRECISE MONITORING OF GUARD POSITION

Detect linear or rotational movement of guards: D4N

Guards and covers on machines protect workers. They limit access to the dangerous parts of the machine. Our safety limit switches guarantee that the guards and covers are in place before the machine is started.

- Wide variety of actuators to fit wide range of applications
- Gold-plated contacts for reliable operation with micro loads
- 1- and 2-conduit models for flexibility in wiring
- M12 connector for fast installation and maintenance





Selection table



Safety limit switches

			Safety limi	it switches	
			The state of the s		
	Model	D4BN	D4N	D4NH	D4NR
eria	Housing	Metal	Plastic	Plastic	Plastic
crit	M12 Plug connector	-		-	-
ţion	Protection class				
Selection criteria	Operating Temperature Range	-40 to 80°C	-30 to 70°C	-30 to 70°C	-30 to 70°C
	Conformity	EN50047, EN1088			
	Conduit size PG13.5				
	Conduit size M20				
	Conduit size G1/2		•	-	•
	Conduit size 1/2-14NPT		-	-	•
	Gold clad contacts	•	-	-	-
	Actuators		_		_
	Resin roller, resin lever		•	-	-
	Resin roller, metal lever		-	-	-
	Metal roller, metal lever Bearing lever, metal lever		-	-	-
	Adj. resin roller, metal lever		=	-	
es	Adj. Rubber roller,		-	-	-
Features	metal lever				_
	Adj. Rod lever Top plunger		-	-	-
	Top roller plunger		-	_	-
	Horizontal roller arm lever		-	_	-
	Vertical roller arm lever		-	_	-
	Cat whisker		-	_	_
	Plastic Rod		•	_	-
	Fork lever lock (right operation)		-	-	-
	Fork lever lock (left operation)	-	•	-	-
	Hinge operation	•	-		-
ation	Position monitoring	•			
Application	General safety application	_	_	-	_
	1NC/1NO snap action			-	-
tion	2NC snap action	-		-	-
ura	1NC/1NO slow action				
Contact configuration	2NC slow action				
3t CO	2NC/1NO slow action				
ntac	3NC slow action		-	_	
පි	1NC/1NO (MBB slow action)		-	-	-
	2NC/1NO (MBB slow action)			040	-
	Page	336	338	340	341



No/not available





Limit switch with metal housing

The D4BN family is a complete line-up of limit switches in metal housing. They are available with two built-in contacts and a wide range of head and actuator types. To set up easy installation and maintenance, various conduit types, e.g. M20, are provided.

- · Direct opening mechanism
- · Various actuators
- · Robust metal housing
- · Gold-plated contacts for handling micro loads
- Metric conduit types available

Ordering information

		Order code				
		Switches (EN50041)		3-conduit Switch		
		1NC/1NO (snap-action)	1NC/1NO (slow-action)	2NC (slow-action)	1NC/1NO (snap-action)	2NC (slow-action)
M	Roller lever	D4B-4111N	D4B-4511N	D4B-4A11N	D4B-8111N	-
	Adjustable roller lever	D4B-4116N	D4B-4516N	D4B-4A16N	D4B-8116N	-
<u>#</u>	Adjustable rod lever	D4B-4117N	D4B-4517N	D4B-4A17N	D4B-8117N	-
Δ	Plain	D4B-4170N	D4B-4570N	D4B-4A70N	-	-
2	Roller	D4B-4171N	D4B-4571N	D4B-4A71N	D4B-8171N	D4B-8A71N
<u>"</u> "	Coil spring	D4B-4181N	-	-	-	-
	Plastic rod	D4B-4187N	-	-	-	-

Note: The above models provide terminal block with M20 conduit. Conduit sizes G1/2 and PG 13.5 are also available.

bold = safety limit switch, mechanical form lock

Item		Snap-action Snap-action	Slow-action		
Durability *1	Mechanical	30,000,000 operations min.	10,000,000 operations min.		
	Electrical	500,000 operations min. (at a 250 VAC, 10 A resistive load)			
Operating speed		1 mm/s to 0.5 m/s			
Operating frequency		Mechanical: 120 operations/min Electrical: 30 operations/min			
Rated frequency		50/60 Hz			
Contact resistance		$25~\mathrm{m}\Omega$ max. (initial value)			
Pollution degree (operating e	nvironment)	3 (EN60947-5-1)			
Conditional short-circuit curr	ent	100 A (EN60947-5-1)			
Conventional enclosed therm	al current (I _{th})	20 A (EN60947-5-1)			
Protection against electric shock		Class I (with ground terminal)			
Ambient temperature		Operating: -40 to 80°C (with no icing) *2			
Degree of protection		IP67 (EN60947-5-1)			

^{*1} The durability is for an ambient temperature of 5 to 35°C and ambient humidity of 40 to 70%. For further conditions, consult your Omron sales representative.
*2 -25 to 80°C for the flexible-rod type.




1NO/1NC contact (snap-action)

If metal deposition between mating contacts occurs on the NC contact side, they can be pulled apart by the shearing force and tensile force generated when part B of the

safety cam or plunger engages part A of the movable contact blade. When the safety cam or plunger is moved in the direction of the arrow, the limit switch releases.


1. When metal deposition occurs.




2. When contacts are being pulled apart.




3. When contacts are completely pulled apart.




1NC/1NO contact (slow-action)



When metal deposition occurs, the contacts are separated from each other by the plunger being pushed in.





Conforms to EN60947-5-1

When metal deposition occurs, the contacts are separated from each other by the plunger being pushed in.

is marked on the product to indicate approval of direct opening.





Limit switch with plastic housing

The D4N-family is a complete line-up of limit switches. They are available with one, two or three built-in contacts and a wide range of head and actuator types. The limit switches intuitive to set up, install and maintain.

- Direct opening mechanism
- Wide range of actuators
- Double insulation
- · Gold-plated contacts for handling micro loads
- . M12 connector terminal blocks (with M20, PG13,5 conduit)

Ordering information

Switches		Connection method		Order code			
				1NC/1NO (snap-action)	1NC/1NO (slow-action)	2NC (slow-action)	2NC/1NO (slow-action)
				Order code	Order code	Order code	Order code
2	Roller lever	1-conduit	M20 ^{*1}	D4N-4120	D4N-4A20	D4N-4B20	D4N-4C20
ব	(resin lever, resin roller)		M12 connector	D4N-9120	D4N-9A20	D4N-9B20	-
		2-conduit	M20 ^{*1}	-	-	-	D4N-8C20
Δ	Plunger	1-conduit	M20 ^{*1}	D4N-4131	D4N-4A31	D4N-4B31	-
			M12 connector	D4N-9131	D4N-9A31	D4N-9B31	-
		2-conduit	M20 ^{*1}	D4N-8131	D4N-8A31	D4N-8B31	-
R	Roller plunger	1-conduit	M20 ^{*1}	D4N-4132	D4N-4A32	D4N-4B32	D4N-4C32
			M12 connector	D4N-9132	D4N-9A32	D4N-9B32	-
		2-conduit	M20 ^{*1}	D4N-8132	D4N-8A32	D4N-8B32	D4N-8C32
	One-way roller arm lever (horizontal)	1-conduit	M20 ^{*1}	D4N-4162	D4N-4A62	D4N-4B62	D4N-4C62
			M12 connector	D4N-9162	D4N-9A62	D4N-9B62	-
		2-conduit	M20 ^{*1}	D4N-8162	D4N-8A62	D4N-8B62	D4N-8C62
	One-way roller arm lever (vertical)	1-conduit	M20 ^{*1}	D4N-4172	D4N-4A72	D4N-4B72	-
	Adjustable roller lever, form lock	1-conduit	M20 ^{*1}	D4N-412G	D4N-4A2G	D4N-4B2G	-
	(metal lever, resin roller)		M12 connector	D4N-912G	D4N-9A2G	D4N-9B2G	-
	Adjustable roller lever, form lock	1-conduit	M20 ^{*1}	D4N-412H	D4N-4A2H	D4N-4B2H	_
	(metal lever, rubber roller)		M12 connector	D4N-912H	D4N-9A2H	D4N-9B2H	-

^{*1.} Conduit sizes 1/2-14NPT, G1/2 and PG13.5 are also available.

bold = safety limit switch, mechanical form lock

Switches with two contacts and MBB contacts

MBB (Make Before Break) contacts have an overlapping structure, so that before the normally closed (NC) contact opens the normally open (NO) contact closes.

Actuator		Connection method		Order code		
				1NC/1NO (slow-action)	2NC/1NO (slow-action)	
٥	Roller lever	1-conduit	M20 ^{*1}	D4N-4E20	D4N-4F20	
(A)	(resin lever, resin roller)		M12 connector	D4N-9E20	-	
		2-conduit	M20 ^{*1}	D4N-8E20	D4N-8F20	
R	Roller plunger	1-conduit	M20 ^{*1}	D4N-4E32	D4N-4F32	
Δ			M12 connector	D4N-9E32	-	
		2-conduit	M20 ^{*1}	D4N-8E32	D4N-8F32	
_@		1-conduit	M20 ^{*1}	D4N-4E62	D4N-4F62	
<u>In</u>			M12 connector	D4N-9E62	-	
		2-conduit	M20 ^{*1}	D4N-8E62	D4N-8F62	

 $^{^{\}star1}$ Conduit sizes 1/2-14NPT, G1/2 and Pg13,5 are also available.



D4N

Specifications


*4					
Durability *1	Mechanical	15,000,000 operations min./Fork lever 10,000,000 operations min.			
	Electrical	500,000 operations min. for a resistive load of 3 A at 250 VAC 300,000 operations min. for a resistive load of 10 A at 250 VAC			
Operating speed		1 mm/s to 0.5 m/s (D4-1120)			
Operating frequency		30 operations/minute max.			
Minimum applicable load	I	Resistive load of 1 mA at 5 VDC (N-level reference value)			
Protection against electr	ic shock	Class II (double insulation)			
Pollution degree (operati	ng environment)	3 (EN60947-5-1)			
Contact gap		Snap-action: 2x0.5 mm min Slow-action: 2x2 mm min			
Conditional short-circuit	current	100 A (EN60947-5-1)			
Rated open thermal current (I _{th})		10 A (EN60947-5-1)			
Ambient temperature		Operating: -30°C to 70°C with no icing			
Degree of protection		IP67 (EN60947-5-1)			

^{*1} The durability is for an ambient temperature of 5°C to 35°C and an ambient humidity of 40 to 70%. For more details, consult your Omron representative.

1NO/1NC contact (snap-action)

If metal deposition between mating contacts occurs on the NC contact side, they can be pulled apart by the shearing force and tensile force generated when part B of the safety cam or plunger engages part A of the movable contact blade. When the safety cam or plunger is moved in the direction of the arrow, the Limit Switch releases.


1. When metal deposition occurs.




Sa

2. When contacts are being pulled apart.

Safety cam directly pushes up the movable contact blade.





1NC/1NO contact (slow-action)



Conforms to EN60947-5-1 direct opening (

When metal deposition occurs, the contacts are separated from each other by the plunger being pushed in.





Conforms to EN60947-5-1 (

When metal deposition occurs, the contacts are separated from each other by the plunger being pushed in.

is marked on the product to indicate approval of direct opening.





Safety door hinge switch

D4NH safety-door hinge switches are available with one or two built-in contacts, shaft or arm lever actuator and various conduit types, e.g. M20.

- Direct opening mechanism
- · Shaft or arm lever actuator
- Wide temperature range
- Metric conduit and M12 connector types are available

Ordering information

Switches	Switches						
Actuator	Conduit size		Built-in switch mechanism				
			1NC/1NO (slow-action)	2NC (slow-action)	2NC/1NO (slow-action)		
Shaft	1-conduit	M20	D4NH-4AAS	D4NH-4BAS	D4NH-4CAS		
		M12 connector	D4NH-9AAS	D4NH-9BAS	-		
	2-conduit	M20	D4NH-8AAS	D4NH-8BAS	D4NH-8CAS		
Arm lever	1-conduit	M20	D4NH-4ABC	D4NH-4BBC	D4NH-4CBC		
		M12 connector	D4NH-9ABC	D4NH-9BBC	-		
	2-conduit	M20	D4NH-8ABC	D4NH-8BBC	D4NH-8CBC		
Actuator	Conduit size		Built-in switch mechanism				
			3NC (slow-action)	1NC/1NO MBB (slow-action)	2NC/1NO MBB (slow-action)		
Shaft	1-conduit	M20	D4NH-4DAS	D4NH-4EAS	D4NH-4FAS		
		M12 connector	-	D4NH-9EAS	-		
Arm lever	1-conduit	M20	D4NH-4DBC	D4NH-4EBC	D4NH-4FBC		
		M12 connector	-	D4NH-9EBC	-		

Note: Conduit types with ${\rm G1/2,\,1/2-14NPT}$ and ${\rm Pg13,5}$ are also available.

Degree of protection		IP67 (EN60947-5-1)		
Durability	Mechanical	1,000,000 operations min.		
	Electrical	500,000 operations min. for a resistive load of 3 A at 250 VAC 300,000 operations min. for a resistive load of 10 A at 250 VAC		
Operating speed		2 to 360°/s		
Operating frequency		30 operations/minute max.		
Protection against electric shock		Class II (double insulation)		
Pollution degree (operating environment)		3 (EN60947-5-1)		
Contact gap		Snap-action: 2x9.5 mm min Slow-action: 2x2 mm min		
Conditional short-circuit current		100 A (EN60947-5-1)		
Rated open thermal current (I _{th})		10 A (EN60947-5-1)		
Ambient temperature		Operating: -30°C to 70°C with no icing		





Safety-limit switch with manual reset

The D4NR family is a complete line-up of safety-limit switches with manual reset. They are available with one, two or three built-in contacts and a wide range of actuator types. To set up easy installation and maintenance, various conduit types, e.g. M20 and M12 connector types, are provided.

- · Direct opening mechanism
- · Various actuators
- · Pull-reset switches
- Gold-plated contacts for handling micro loads
- Metric conduit types available

Ordering information

Switches		Conduit size		Order code	
				Built-in switch mechanism	
				1NC/1NO (slow-action)	2NC/1NO (slow-action)
Roller lever (resin lever, r		1-conduit	M20	D4N-4A20R	D4N-4C20R
	(resin lever, resin roller)		M12 connector	D4N-9A20R	-
		2-conduit	M20	D4N-8A20R	D4N-8C20R
	Adjustable roller lever, form lock	1-conduit	M20	D4N-4A2HR	D4N-4C2HR
	(metal lever, rubber roller)		M12 connector	D4N-9A2HR	-
Est .		2-conduit	M20	D4N-8A2HR	D4N-8C2HR
A	Plunger	1-conduit	M20	D4N-4A31R	D4N-4C31R
			M12 connector	D4N-9A31R	-
		2-conduit	M20	D4N-8A31R	D4N-8C31R
R	Roller plunger	1-conduit	M20	D4N-4A32R	D4N-4C32R
			M12 connector	D4N-9A32R	-
		2-conduit	M20	D4N-8A32R	D4N-8C32R

Note: Conduit types with G1/2, 1/2-14NPT and Pg13,5 are also available.

Degree of protection		IP67 (EN60947-5-1)		
Durability Mechanical		1,000,000 operations min.		
	Electrical	500,000 operations min. for a resistive load of 3 A at 250 VAC 300,000 operations min. for a resistive load of 10 A at 250 VAC		
Operating speed		1 mm/s to 0.5 m/s (D4N-1A20R)		
Operating frequency		30 operations/minute max.		
Protection against electric shock		Class II (double insulation)		
Pollution degree (operating environment)		3 (EN60947-5-1)		
Contact gap		Snap-action: 2×0.5 mm min Slow-action: 2×2 mm min		
Rated open thermal current (I _{th})		10 A (EN60947-5-1)		
Ambient temperature		Operating: -30°C to 70°C with no icing		





BREAK CONVENTIONAL BARRIERS IN SAFETY DESIGN

Flexibility selecting best fit control device for non-contact switch application: F3S-TGR-N

Omron has introduced a series of magnetic coded contactless switches for interlocking machine guard doors. The switches feature a built-in control function, thus saving the cost and space required for an external controller. The non-contact switches offer advantages in applications where a precise approach of the guard and lock is not possible. Applications with a large amount of dirt or high hygienic standards can also be addressed.

- Operates with all Omron safety relay units and safety bus interfaces
- · Operates behind stainless steel fittings
- Non-contact no abrasion no particles
- Conforms to safety categories up to 4 acc. EN 954-1 and PDF-M acc. EN60947-5-3





		Safety doo	r switches	Non-contact safety door switches		
			()	100	The same of the sa	100
	Model	D4NS	D4BS	D40A/G9SX-NS	F3S-TGR-N_C	F3S-TGR-N_R
<u>=</u>	Housing	Plastic	Metal	Plastic	Plastic/Metal	Plastic/Metal
Selection criteria	Head mounting	4 directions	4 directions	-	-	-
io	Actuation	Straight	Straight	-	-	-
lect	Key holding force	-	-	-	-	-
Se	Protection class					
	Conformity		_	EN 954-1	EN954-1, EN60947-5-3	EN954-1, EN60947-5-3
	Conduit size PG13.5		_	-	-	-
	Conduit size M20	•	-	-	-	-
	Conduit size G1/2		-	-	-	-
	Conduit size 1/2-14NPT		•	_	-	-
	Cable length 2 m Cable length 5 m	-	-	-	-	
	Cable length 10 m		_	_	-	
	Connector type M12		_	_	-	-
	Gold clad contacts		_	_	_	-
	Operation key horizontal		-	_	_	_
S	Operation key vertical		_	_	_	_
Features	Operation key adjustable horizontal			_	_	_
Fea	Operation key adjustable horizontal and vertical		_	_	_	-
	Mechanical lock/24 VDC solenoid release	-	_	_	_	_
	Mechanical lock/110 VAC solenoid release	-	_	_	_	-
	Mechanical lock/230 VAC solenoid release	-	_	_	_	_
	24 VDC solenoid lock/mechanical release	_	_	-	-	-
	110 VAC solenoid lock mechanical release	-	-	-	-	-
	240 VAC solenoid lock mechanical release	-	-	-	-	-
	High temperature Sensor	-	-	-		
	operates with G9SA, G9SB			-		
	operates wit h G9SX					
	operates with programmable safety units NE1A			-		•
Application	Door monitoring	•	•	-	•	
Appli	Door locking		-	-	-	-
	1NC/1NO	_	_		-	-
	1NC/1NO SL		•	-	-	-
	1NC/NO SL			-	-	_
	2NC		-	-	•	•
	2NC SL		•	-	-	-
	2NC/1NO 2NC/1NO SL		_	-	-	-
	2NG/TNO SE		_	_	_	-
	3NC SL		_	-	_	-
Contact configuration	1NC/1NO (MBB contact)		_	_	_	-
Jura	2NC/1NO (MBB contact)		_	_	_	-
Julie	1NO/1NC		-	-	-	-
ct	2NO/1NC		-	-	-	-
onta	1NC/1NO SL + 1NC/1NO SL	-	_	_	_	-
3	1NC/1NO SL + 2NC SL	-	-	-	-	-
	1NC/1NO SL + 1NC SL	-	-	-	-	-
	2NC SL + 1NC/1NO SL	-	-	-	-	-
	2NC/1NO SL + 1NC/1NO SL		-	-	-	-
	2NC/1NO SL + 2NC SL		-	-	-	-
	2NC SL + 2NC SL	-	-	-	-	-
	2NC SL + 1NC SL		-	-	-	-
	3NC SL + 1NC/1NO SL		-	-	-	-
	3NC SL + 2NC SL		-	_	-	-
	Page	350	351	380	352	354



			Safety door lock switche	S
				- A
	Model	D4NL	D4GL	D4BL
eria	Housing	Plastic	Plastic	Metal
ı crii	Head mounting Actuation	4 directions Straight	4 directions Straight	4 directions Straight
Selection criteria	Key holding force	1,300 N	1,000 N	700 N
Sele	Protection class	IP67	1,000 11	
	Conformity	EN1088	EN1088	EN1088
	Conduit size PG13.5			
	Conduit size M20	_		
	Conduit size G1/2	•	•	•
	Conduit size 1/2-14NPT	-	-	-
	Cable length 2 m Cable length 5 m	_	_	_
	Cable length 10 m	_	_	-
	Connector type M12		-	-
	Gold clad contacts	•	•	•
	Operation key horizontal			
res	Operation key vertical			
Features	Operation key adjustable horizontal			
Ψ.	Operation key adjustable horizontal and vertical		•	-
	Mechanical lock/24 VDC solenoid release Mechanical lock/110 VAC solenoid release			H
	Mechanical lock/210 VAC solenoid release		_	-
	24 VDC solenoid lock/mechanical release			
	110 VAC solenoid lock mechanical release		_	-
	240 VAC solenoid lock mechanical release	•	-	-
	High temperature Sensor	-	-	-
	operates with G9SA, G9SB			
	operates wit h G9SX		-	-
	operates with programmable safety units NE1A	_	-	-
Application	Door monitoring Door locking	:		
App				
	1NC/1NO 1NC/1NO SL		_	
	1NC/NO SL		-	-
	2NC		_	-
	2NC SL		-	-
	2NC/1NO		-	-
	2NC/1NO SL		-	-
	3NC		-	-
ion	3NC SL 1NC/1NO (MBB contact)		-	-
Contact configuration	2NC/1NO (MBB contact)		-	-
onfig	1NO/1NC		_	_
ct cc	2NO/1NC		-	-
onta	1NC/1NO SL + 1NC/1NO SL			-
చ	1NC/1NO SL + 2NC SL		•	-
	1NC/1NO SL + 1NC SL		-	
	2NC SL + 1NC/1NO SL			-
	2NC/1NO SL + 1NC/1NO SL		-	-
	2NC/1NO SL + 2NC SL 2NC SL + 2NC SL			-
	2NC SL + 2NC SL 2NC SL + 1NC SL		-	-
	3NC SL + 1NC/1NO SL		•	-
	3NC SL + 2NC SL			-
	Page		348	349
	1 490			

■ Standard

No/not available







Guard-lock safety door switch

The D4NL guard-lock safety-door switches are available with four or five built-in contacts. When locked, they have a key holding force of up to 1300N. Mechanical lock/solenoid release types and vice versa set up the complete range in combination with various conduit types, e.g. M20.

- · Safety-door switch with electromagnetic lock or unlock mechanism
- · Models with four or five built-in contacts
- · Strong key holding force: 1300N
- For standard loads and micro loads
- Keys are compatible with D4GL and D4NS

Ordering information

Switches (with approved direct opening contacts)

For 110V and 230V version ask your local Omron representative

Lock and release types	Contact configuration	Conduit opening	Order code
Mechanical lock	1NC/1NO + 1NC/1NO	M20	D4NL-4AFA-B
solenoid release	1NC/1NO + 2NC	M20	D4NL-4BFA-B
	2NC + 1NC/1NO	M20	D4NL-4CFA-B
	2NC + 2NC	M20	D4NL-4DFA-B
	2NC/1NO + 1NC/1NO	M20	D4NL-4EFA-B
	2NC/1NO + 2NC	M20	D4NL-4FFA-B
	3NC + 1NC/1NO	M20	D4NL-4GFA-B
	3NC + 2NC	M20	D4NL-4HFA-B

Lock and release types	Contact configuration	Conduit opening	Order code
Solenoid lock	1NC/1NO + 1NC/1NO	M20	D4NL-4AFG-B
mechanical release	1NC/1NO + 2NC	M20	D4NL-4BFG-B
Telease	2NC + 1NC/1NO	M20	D4NL-4CFG-B
	2NC + 2NC	M20	D4NL-4DFG-B
	2NC/1NO + 1NC/1NO	M20	D4NL-4EFG-B
	2NC/1NO + 2NC	M20	D4NL-4FFG-B
	3NC + 1NC/1NO	M20	D4NL-4GFG-B
	3NC + 2NC	M20	D4NL-4HFG-B

Note: - Conduit sizes of G1/2 and Pg 13,5 are also available.

Operation keys (order separately)

Туре	Order code
Horizontal mounting	D4DS-K1
Vertical mounting	D4DS-K2

Туре	Order code
Adjustable mounting (horizontal)	D4DS-K3
Adjustable mounting (horizontal/vertical)	D4DS-K5

Specifications

Degree of protection		IP67 (EN60947-5-1) (This applies for the switch only. The degree of protection for the key hole is IP00.)
Durability*1	Mechanical	1,000,000 operations min.
	Electrical	500,000 operations min. for a resistive load of 3 A at 250 VAC
Operating speed		0.05 to 0.5 m/s
Operating frequency		30 operations/minute max.
Rated frequency		50/60 Hz
Contact gap		2x2 mm min
Direct opening force *2		60 N min. (EN60947-5-1)
Direct opening travel *2		10 mm min. (EN60947-5-1)
Holding force		1,300 N min.
Minimum applicable	load	Resistive load of 1 mA at 5 VDC (N-level reference value)
Thermal current (I _{th})		10 A (EN60947-5-1)
Conditional short-circuit current		100 A (EN60947-5-1)
Pollution degree (operating environment)		3 (EN60947-5-1)
Protection against electric shock		Class II (double insulation)
Ambient temperature	e	Operating: -10°C to 55°C (with no icing or condensation)

^{*1} The durability is for an ambient temperature of 5°C to 35°C and an ambient humidity of 40 to 70%. For more details, consult your Omron representative.
*2 These figures are minimum requirements for safe operation.

Note: The above values are initial values.



⁻ Solenoid: 24 VDC, Orange LED: 10 to 115 VAC/VDC



Guard-lock safety door switch

The D4GL guard-lock safety-door switches are available with four or five built-in contacts. When locked, they have a key holding force of up to 1000 N. Mechanical lock/solenoid release types and vice versa set up the complete range in combination with various conduit types, e.g. M20.

- · Slim safety-door switch with electromagnetic lock or unlock mechanism
- · Models with four or five built-in contacts
- Strong key holding force: 1000 N
- · For standard loads and micro loads
- Keys are compatible with D4NL and D4NS

Ordering information

Switches (with approved direct opening contacts)

Lock and release types	Contact configuration	Conduit size	Order code
Mechanical lock	1NC/1NO + 1NC/1NO	M20	D4GL-4AFA-A
solenoid release	1NC/1NO + 2NC	M20	D4GL-4BFA-A
	2NC + 1NC/1NO	M20	D4GL-4CFA-A
	2NC + 2NC	M20	D4GL-4DFA-A
	2NC/1NO + 1NC/1NO	M20	D4GL-4EFA-A
	2NC/1NO + 2NC	M20	D4GL-4FFA-A
	3NC + 1NC/1NO	M20	D4GL-4GFA-A
	3NC + 2NC	M20	D4GL-4HFA-A

Lock and release types	Contact configuration	Conduit size	Order code
Solenoid lock	1NC/1NO + 1NC/1NO	M20	D4GL-4AFG-A
mechanical	1NC/1NO + 2NC	M20	D4GL-4BFG-A
release	2NC + 1NC/1NO	M20	D4GL-4CFG-A
	2NC + 2NC	M20	D4GL-4DFG-A
	2NC/1NO + 1NC/1NO	M20	D4GL-4EFG-A
	2NC/1NO + 2NC	M20	D4GL-4FFG-A
	3NC + 1NC/1NO	M20	D4GL-4GFG-A
	3NC + 2NC	M20	D4GL-4HFG-A

Note: - conduit sizes of G1/2 and Pg13,5 are also available.

- solenoid: 24 VDC, orange/green LED: 24 VDC

Operation keys (order separately)

Туре		Order code
Horizontal mounting	2	D4DS-K1
Vertical mounting		D4DS-K2

Туре	Order code
Adjustable mounting (horizontal)	D4DS-K3
Adjustable mounting (horizontal/vertical)	D4DS-K5

Specifications

Degree of protection		IP67 (EN60947-5-1) (This applies for the switch only. The degree of protection for the key hole is IP00.)	
Durability *1	Mechanical	1,000,000 operations min.	
	Electrical	500,000 operations min. for a resistive load of 4 mA at 24 VDC; 150,000 operations min. for a resistive load of 1 A at 125 VAC in 2 circuits and 4 mA at 24 VDC in 2 circuits	
Operating speed		0.05 to 0.5 m/s	
Operating frequency		30 operations/minute max.	
Rated frequency		50/60 Hz	
Contact gap		2x2 mm min.	
Direct opening force	*2	60 N min. (EN60947-5-1)	
Direct opening travel *3		10 mm min. (EN60947-5-1)	
Holding force		1,000 N min.	
Minimum applicable	load	Resistive load of 4 mA at 24 VDC (N-level reference value)	
Thermal current (Ith)		2.5 A (EN60947-5-1)	
Conditional short-circuit current		100 A (EN60947-5-1)	
Pollution degree (operating environment)		3 (EN60947-5-1)	
Protection against electric shock		Class II (double insulation)	
Ambient temperature	е	Operating: -10°C to 55°C with no icing	

¹ The durability is for an ambient temperature of 5°C to 35°C and an ambient humidity of 40 to 70%. For more details, consult your Omron representative.

*3 These figures are minimum requirements for safe operation.

Note: The above values are initial values.



^{*2} These figures are minimum requirements for safe operation.



Guard-lock safety door switch with metal housing

The D4BL guard-lock safety-door switches are available with three built-in contacts. They are mechanically locked when the key is inserted and have a solenoid release. An auxiliary release key ensures easy maintenance and unlocks the door in case of power failure.

- Automatically mechanical lock
- · Auxiliary release key for easy maintenance
- · Tough aluminium die-cast body
- · Horizontal and vertical conduit opening
- · Head direction can easily be changed

Ordering information

Switches						
	Conduit size	Voltage for solenoid	Without indicator 1NC/1NO+ 1NC (slow-action)	With LED indicator 1NC/1NO+ 1NC (slow-action)	Without indicator 2NC+ 1NC (slow-action)	With LED indicator 2NC+ 1NC (slow-action)
Mechanical lock	PG13.5	24 VDC	D4BL-1CRA	D4BL-1CRA-A	D4BL-1DRA	D4BL-1DRA-A
		110 VAC	D4BL-1CRB	D4BL-1CRB-A	D4BL-1DRB	D4BL-1DRB-A
	M20	24 VDC	D4BL-4CRA	D4BL-4CRA-A	D4BL-4DRA	D4BL-4DRA-A
		110 VAC	D4BL-4CRB	D4BL-4CRB-A	_	_
Solenoid lock	Pg 13.5	24 VDC	D4BL-1CRG	D4BL-1CRG-A	D4BL-1DRG	D4BL-1DRG-A
	M20	24 VDC	_	D4BL-4CRG-A	_	_

Operation keys (order separately)

Туре		Order code
Horizontal mounting		D4BL-K1
Vertical mounting	** 0	D4BL-K2

Туре	Order code
Adjustable mounting (horizontal)	D4BL-K3

Specifications

Degree of protection	IP67 (EN60947-5-1)	
Durability*1	Mechanical: 1,000,000 operations min. Electrical: 500,000 operations min. (10 A resistive load at 250 VAC)	
Operating speed	0.05 to 0.5 m/s	
Operating frequency	30 operations/min max.	
Rated frequency	50/60 Hz	
Operating characteristics Direct opening force: 19.61 N min. (EN60947-5-1) Direct opening travel: 20 mm min. (EN60947-5-1) All stroke: 23 mm min.		
Holding force 700 N min. (GS-ET-19)		
Thermal current (I _{th})	10 A (EN60947-5-1)	
Pollution degree 3 (EN60947-5-1) (operating environment)		
Protection against electric shock Class I (with ground terminal)		
Ambient temperature	Operating: -10 to 55°C (with no icing)	

 $^{^{\}star1}$ The durability is for an ambient temperature of 5 to 35°C and an ambient humidity of 40 to 70%.

Note: The above values are initial values.

Solenoid coil characteristics

Item	24 VDC mechanical lock models	110 VAC mechanical lock models	24 VAC solenoid lock models	
Rated operating voltage	24 VDC ^{+10%} / _{-15%} (100% ED)	110 VAC ±10% (50/60 Hz)	24 VDC ^{+10%} / _{-15%} (100% ED)	
Current consumption	Approx. 300 mA	Approx. 98 mA	Approx. 300 mA	
Indicator characteristics				

Item	LED
Rated voltage	10 to 115 VAC/VDC
Current leakage	Approx. 1 mA
Color (LED)	Orange, green





Safety door switch with plastic housing

The D4NS line-up includes three-contact models with 2NC/1NC and 3NC contact forms in addition to the previous contact forms, 1NC/1NO and 2NC. Models with M12 connectors and conduit opening, such as M20, are also available.

- Line-up with three contacts: 2NC/1NC and 3NC contact forms
- Line-up with two contacts 1NC/1NO and 2NC
- . M12 connector types available
- · Standardised gold-clad contacts for high contact reliability
- · Applicable for standard loads and micro loads

Ordering information

Switches (with approved direct opening contacts)

Туре	Contact configuration		Conduit opening/connector	Order code
1-conduit	Slow-action	1NC/1NO	M20	D4NS-4AF
		2NC	M20	D4NS-4BF
		2NC/1NO	M20	D4NS-4CF
		3NC	M20	D4NS-4DF
	Slow-action MBB contact	1NC/1NO	M20	D4NS-4EF
		2NC/1NO	M20	D4NS-4FF
2-conduit	Slow-action	1NC/1NO	M20	D4NS-8AF
		2NC	M20	D4NS-8BF
		2NC/1NO	M20	D4NS-8CF
	Slow-action MBB contact	1NC/1NO	M20	D4NS-8EF
	Slow-action MBB contact	2NC/1NO	M20	D4NS-8FF
1-conduit,	Slow-action	1NC/1NO	M12 connector	D4NS-9AF
with connector		2NC	M12 connector	D4NS-9BF
	Slow-action MBB contact	1NC/1NO	M12 connector	D4NS-9EF

Note: Additionally conduit sizes G1/2, 1/2-14NPT and Pg13,5 are available.

Operation keys (order separately)

Туре		Order code
Horizontal mounting	2	D4DS-K1
Vertical mounting	**	D4DS-K2

Туре	Order code
Adjustable mounting (horizontal)	D4DS-K3
Adjustable mounting (horizontal/vertical)	D4DS-K5

Specifications

Degree of protection		IP67 (EN60947-5-1) (This applies for the switch only. The degree of protection for the key hole is IP00.)		
Durability *1	Mechanical	1,000,000 operations min.		
	Electrical	500,000 operations min. for a resistive load of 3 A at 250 VAC 300,000 operations min. for a resistive load of 10 A at 250 VAC		
Operating speed		0.05 to 0.5 m/s		
Operating frequency		30 operations/minute max.		
Direct opening force *2		60 N min.		
Direct opening travel *2		10 mm min.		
Minimum applicable lo	ad	Resistive load of 1 mA at 5 VDC (N-level reference value)		
Protection against elec	etric shock	Class II (double insulation)		
Pollution degree (operation	ating environment)	3 (EN60947-5-1)		
Contact gap		2×2 mm min		
Conditional short-circuit current		100 A (EN60947-5-1)		
Rated open thermal current (I _{th})		10 A (EN60947-5-1)		
Ambient temperature		Operating: -30°C to 70°C with no icing		

^{*1} The durability is for an ambient temperature of 5°C to 35°C and an ambient humidity of 40 to 70%. For more details, consult your Omron representative.

Note: The above values are initial values.



These figures are minimum requirements for safe operation.



Safety door switch with metal housing

The D4BS line-up includes two-contact models with 1NC/1NO and 2NC in a robust metal housing. 1 or 3 conduit openings, such as M20 or PG13,5 are available.

- · Robust metal housing
- Line-up with two contacts: 1NC/1NO and 2NC
- Standardised gold-clad contacts for high contact reliability
- Applicable for standard loads and micro loads

Ordering information

Switches

Туре	Mounting direction	Conduit size	Order code	
			1NC/1NO (slow-action)	2NC (slow-action)
1-conduit	Front-side mounting	Pg13.5	D4BS-15FS	D4BS-1AFS
		M20	D4BS-45FS	D4BS-4AFS
3-conduit		Pg13.5	D4BS-55FS	D4BS-5AFS
		M20	D4BS-85FS	D4BS-8AFS

Operation keys (order separately)

- p,- (,,			
Туре		Order code	
Horizontal mounting	*	D4BS-K1	
Vertical mounting	000	D4BS-K2	
Adjustable mounting (horizontal)		D4BS-K3	

Specifications

Degree of protection*1	IP67 (EN60947-5-1)
Durability*2	Mechanical: 1,000,000 operations min. Electrical: 500,000 operations min. (10 A at 250 VAC, resistive load)
Operating speed	0.1 m/s to 0.5 m/s
Operating frequency	30 operations/min max.
Rated frequency	50/60 Hz
Contact gap	2×2 mm min.
Direct opening force*3	19.61 N min. (EN60947-5-1)
Direct opening travel*3	20 mm min. (EN60947-5-1)
Full stroke	23 mm min.
Conventional enclosed thermal current (I _{th})	20 A (EN60947-5-1)
Conditional short-circuit current	100 A (EN60947-5-1)
Pollution degree (operating environment)	3 (EN60947-5-1)
Protection against electric shock	Class I (with ground terminal)
Ambient temperature	Operating: -40 to 80°C (with no icing)

Although the switch box is protected from dust, oil, or water penetration, do not use the D4BS in places where dust, oil, water, or chemicals may penetrate through the key hole on the head, otherwise switch damage or malfunctioning may occur.


The durability is for an ambient temperature of 5°C to 35°C and an ambient humidity of 40 to 70%. Contact your Omron sales representative for more detailed information on other operating envi-

Note: The above values are initial values.



ronments.

*3 These figures are minimum requirements for safe operation.



Non-contact switches for monitoring the status of guarding doors

Non-contact switches monitor the status of guarding doors. LED for easy diagnosis and stainless steel housing for high hygiene demands in the food industry are available

- Operates with all Omron safety controllers
- · Operates behind stainless steel fittings
- Non-contact no abrasion no particles
- Screw-hole covers support hygienic design (NMPC)
- Conforms to safety categories up to 4 acc. EN 954-1, PDF-M acc. EN60947-5-3 and PLe acc. EN ISO13849-1

Ordering information

Elongated sensors

Cable connection	Contact configuration	Order code
2 m pre-wired	2NC/1NO	F3S-TGR-NLPC-21-02
5 m pre-wired	2NC/1NO	F3S-TGR-NLPC-21-05
10 pre-wired	2NC/1NO	F3S-TGR-NLPC-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NLPC-21-M1J8

Small sensors

Cable Connection	Contact configuration	Order code
2 m pre-wired	2NC/1NO	F3S-TGR-NSMC-21-02
5 m pre-wired	2NC/1NO	F3S-TGR-NSMC-21-05
10 pre-wired	2NC/1NO	F3S-TGR-NSMC-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NSMC-21-M1J8

Miniature sensors

Cable connection	Contact configuration	Order code
2m pre-wired	2NC/1NO	F3S-TGR-NMPC-21-02
5m pre-wired	2NC/1NO	F3S-TGR-NMPC-21-05
10m pre-wired	2NC/1NO	F3S-TGR-NMPC-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NMPC-21-M1J8

Specifications

Mechanical data

Item	Model	Elongated sensor	Small sensor	Miniature sensor
Operating distance	OFF → ON (Sao)	12 mm Close		8 mm Close
	ON → OFF (Sar)	17 mm Open		12 mm Open
Actuator approach speed	Min. Max.	4 mm/s 1000 mm/s		
Operating temperature	-	-25°C to +80°C	-25°C to +105°C	-25°C to +80°C
Enclosure protection	Flying lead M12 connector	IP 67		
Material	-	Black Polycarbonate	Stainless steel 316	Black Polyester



F3S-TGR-N_C

Electrical data Item Model **Elongated sensor** Small sensor Miniature sensor 24 VDC ±15% Power supply Power consumption Max. 50 mA 10 mA, 10 VDC Switching current Min. 100 mA, 24 VDC 100 mA, 24 VDC NC contacts NO contact Rated loads Max.


Electronic output (potential-free optocoupler output)


Approved standards

Output type

EN standards certified by TÜV Rheinland
EN 954-1, EN ISO13849-1
EN 60204-1
EN/IEC 60947-5-3
UL 508, CSA C22.2
BS 5304
EN 1088-1 conformance

Wiring examples (Single head connection up to category 4 acc. EN954-1)





Non-contact switches for monitoring the status of guarding doors

Non-contact switches monitor the status of guarding doors. LED for easy diagnosis and stainless steel housing for high hygiene demands in the food industry are available.

- Operates with all Omron safety controllers
- · Operates behind stainless steel fittings
- Non-contact no abrasion no particles
- Screw-hole covers support hygienic design (NMPR)
- Conforms to safety categories up to 4 acc. EN 954-1, PDF-M acc. EN60947-5-3 and PLe acc. EN ISO13849-1

Ordering information

Elongated sensors

Cable connection	Contact configuration	Order code
2 m pre-wired	2NC/1NO	F3S-TGR-NLPR-21-02
5 m pre-wired	2NC/1NO	F3S-TGR-NLPR-21-05
10 pre-wired	2NC/1NO	F3S-TGR-NLPR-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NLPR-21-M1J8

Small sensors

Cable connection	Contact configuration	Order code
2 m pre-wired	2NC/1NO	F3S-TGR-NSMR-21-02
5 m pre-wired	2NC/1NO	F3S-TGR-NSMR-21-05
10 pre-wired	2NC/1NO	F3S-TGR-NSMR-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NSMR-21-M1J8

Miniature sensors

Cable connection	Contact configuration	Order code
2m pre-wired	2NC/1NO	F3S-TGR-NMPR-21-02
5m pre-wired	2NC/1NO	F3S-TGR-NMPR-21-05
10m pre-wired	2NC/1NO	F3S-TGR-NMPR-21-10
M12, 8-pin	2NC/1NO	F3S-TGR-NMPR-21-M1J8

Specifications

Mechanical data

Item	Model	Elongated sensor	Small sensor	Miniature sensor
Operating distance	OFF → ON (Sao)	10 mm Close		12 mm Close
	ON → OFF (Sar)	22 mm Open		20 mm Open
Actuator approach speed	Min. Max.	4 mm/s 1000 mm/s		
Operating temperature	-	-25°C to +80°C	-25°C to +105°C	-25°C to +80°C
Enclosure protection	Flying lead M12 connector	IP 67		
Material	-	Black Polycarbonate	Stainless steel 316	Black Polyester



F3S-TGR-N_R


Electrical data

Item		Model	Elongated sensor	Small sensor	Miniature sensor
Contact release time		Max.	2 ms		
Initial contact resistance		Max.	50 m $Ω$		500 m $Ω$
Switching current		Min.	1 mA, 10 VDC		10 mA, 10 VDC
Rated loads	NC contacts NO contact	Max.	1 A, 250 VAC 0.2 A, 24 VDC		0.5 A, 250 VAC 0.2 A, 24 VDC

Approved standards

EN standards certified by TÜV Rheinland	
EN 954-1, EN ISO13849-1	
EN 60204-1	
EN/IEC 60947-5-3	
UL 508, CSA C22.2	
BS 5304	
EN 1088-1 conformance	

Wiring examples (Single head connection up to category 4 acc. EN954-1)




PROTECT OPERATORS AND PRODUCTION

Total consistency across the board

Safety Sensors are the first choice in safeguarding workplaces where persons and machines cooperate. Built-in intelligence stops the machine in conditions that are dangerous for the worker. Our F3S-TGR-CL range offers safety light curtains with included safe control functions for finger-, hand- and body protection, all using the same concept of wiring, installation and setup for simplicity in daily use and maintenance.

- Finger- and Hand and body protection models
- · Control functions included
- X-, T- and L-muting
- fixed and floating blanking
- single and double break operation
- pre-reset access control
- Easy mounting and common wiring for all types for simple design and installation
- Certified acc. EN61496 and EN ISO 13849-1.





Selection table

		Safety Sensors							
				1					
	Model	MS2800 & MS4800	F3S-TGR-CL	F3SN-A	F3S-B				
	Safety category	Category 2&4	Category 2&4	Category 4	Category 2				
Selection criteria	Safety Integrity Level (IEC 61508)	SIL 3	-	-	-				
crit	Protective height	280 to 2120 mm	150 to 2400 mm	189 to 1,807 mm	300 to 1650 mm				
tion	Resolution	14, 30 mm	14, 35 mm	14, 25, 40, 70 mm	30, 55, 80 mm				
elec	Beam pitch	10, 20 mm	7.5, 18 mm	9, 15, 30, 60 mm	25, 50, 70 mm				
Š	Reaction time	14 to 59 ms	14 to 103 ms	10 to 15.5 ms	20 to 45 ms				
	Temperature range	-10 to 55°C	-10 to 55°C	-10 to 55°C	-10 to 55°C				
	IP class	IP65	IP65	IP65	IP65				
	Blanking function	internal	internal	internal	option				
	Muting function	option	internal	-	-				
	EDM function	internal	internal	internal	internal				
Features	Interlock function	internal	internal	internal	internal				
eat	Series connection	option	option	option	option				
_	Mounting kits	option	option	option	option				
	Parameter setting	internal DIP switch	internal DIP switch	option (Console)	option (PC)				
	External control unit	-	-	-	-				
	Finger protection		-	•	-				
	Hand protection	•	•	•					
Ë	Arm protection	•	•	•	•				
lica	Body protection	•	•	•					
Application	Presence detection								
	Muting application	-	•	-	-				
	Blanking application		•	•					
Supply voltage	24 VDC	•	•	•	•				
	Safety outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs				
outs	Auxiliary output	1 PNP (non safety)	-	2 PNP (non safety)	1 PNP (non safety)				
and Outputs	Test input				•				
nd (EDM input				-				
= =	Reset input				-				
_	Muting sensor input	-		-	-				
	Page	361	365	363	360				



		Safety Sensors							
	Model	E3FS + F3SP-U3P	F3S-TGR-CLK_	F3S-TGR-CLK_C	0\$32C				
	Safety category	* *	Category 2 and 4	Category 2 and 4	Category 3				
Selection criteria	Safety Integrity Level (IEC 61508)	-	-	-	SIL 2				
G	Protective height	-	500 to 1.200 mm	500 to 1.200 mm	Scanning range 3 m				
景	Resolution	-	-	-	-				
e e	Beam pitch	-	300 mm, 400 mm, 500 mm	300 mm, 400 mm, 500 mm	-				
S	Reaction time	32 ms	13 ms	13 ms	80 ms				
	Temperature range	-10 to 55°C	-10 to 55°C	-10 to 55°C	-10 to 50°C				
	IP class	IP67	IP65	IP65	IP65				
	Blanking function	-	-	-	-				
	Muting function	·	internal	internal	-				
S	EDM function		internal	internal	internal				
Features	Interlock function	option	internal	internal	internal				
Feat	Series connection	-	-	-	-				
	Mounting kits		option	option	option				
	Parameter setting		internal DIP switch	internal DIP switch	Software (included)				
	External control unit		-	-	-				
	Finger protection		-	-	-				
	Hand protection	-	-	-	-				
i i	Arm protection		-	-	-				
Application	Body protection								
App	Presence detection		-	-					
	Muting application				-				
	Blanking application		-	-	-				
Supply voltage	24 VDC		•	•					
	Safety outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs	2 PNP OSSD transistor outputs				
puts	Auxiliary output		-	-					
In- and Outputs	Test input				-				
and	EDM input	-							
<u>=</u>	Reset input								
	Muting sensor input				-				
	Page	372	365	365	369				



Safety sensors



Category-2 safety light curtain

The F3S-B is a category-2 safety light curtain with resolutions of 30, 55 and 80 mm. An operating range of up to 5 m and protective heights from 300mm to 1,650 mm are provided with a very small dead zone.

- Sensing distance up to 5 m
- LEDs for easy alignment and diagnosis
- Series connection of two sensors is possible
- Category-2 sensor complying with EN 61496-1, EN 954-1 and EN ISO 13849-1

Ordering information

Optical resolution	No. of optical axes	Protective height	Order code
30 mm	12	300 mm	F3S-B122P
	18	450 mm	F3S-B182P
	24	600 mm	F3S-B242P
	30	750 mm	F3S-B302P
	36	900 mm	F3S-B362P
	42	1,050 mm	F3S-B422P
	48	1,200 mm	F3S-B482P
	54	1,350 mm	F3S-B542P
	60	1,500 mm	F3S-B602P
	66	1,650 mm	F3S-B662P
55 mm	6	300 mm	F3S-B065P
	9	450 mm	F3S-B095P
	12	600 mm	F3S-B125P
	15	750 mm	F3S-B155P
	18	900 mm	F3S-B185P

Optical resolution	No. of optical axes	Protective height	Order code
55 mm	21	1,050 mm	F3S-B215P
	24	1,200 mm	F3S-B245P
	27	1,350 mm	F3S-B275P
	30	1,500 mm	F3S-B305P
	33	1,650 mm	F3S-B335P
80 mm	4	300 mm	F3S-B047P
	6	450 mm	F3S-B067P
	8	600 mm	F3S-B087P
	10	750 mm	F3S-B107P
	12	900 mm	F3S-B127P
	14	1,050 mm	F3S-B147P
80 mm	16	1,200 mm	F3S-B167P
	18	1,350 mm	F3S-B187P
	20	1,500 mm	F3S-B207P
	22	1,650 mm	F3S-B227P

Specifications

Item	F3S-BP ^{*1} Stand-alone			F3S-BMP*1 Master unit for series connection			F3S-BS*1 Slave unit for series connection		
Sensor type	Type 2 Safety I	Type 2 Safety Light Curtain							
Optical-axis pitch	25 mm	50 mm	75 mm	25 mm	50 mm	75 mm	25 mm	50 mm	75 mm
Optical resolution	Non-transparer	nt: In diameter							
(Detection capability)	30 mm	55 mm	80 mm	30 mm	55 mm	80 mm	30 mm	55 mm	80 mm
Protective height	300/450/600/7	'50/900/1,050/	1,200/1,350/1,50	0/1,650 mm			300/450/600	/750 mm	
Detection distance	0.3 to 5.0 m								
Response time		ON to OFF 20 ms to 45 ms (stand-alone) ON to OFF 20 ms to 65 ms (series connection)							
Supply voltage (Vs)	24 VDC ±20%	(including 5 Vp-	-p ripple)						
Current consumption	400 mA max. (under no-load o	conditions)						
Light source	Infrared LED (8	80 nm wavelen	igth).						
Effective aperture angle	Within ±5° for	the emitter and	receiver at a det	ection distance	of at least 3 m a	according to IEC	61496-2		
Control output	Two PNP trans	istor outputs, lo	ad current 200 m	A max.					
Instability output	PNP transistor	output (non safe	ety output)						
Protection circuit	Output short-ci	rcuit protection	, power supply re	verse connectio	n protection				
External test function	Active: 17 VDC	to Vs, 10 mA m	"External test inp nax. duration time 2.5 VDC, 2 mA n	at least 15 ms					
Relay monitoring function (optional)	Default inactive	e, selectable wit	th F39-U1E						
Start interlock function (optional)	Default inactive	e, selectable wit	th F39-U1E						
Blanking function (optional)	Default inactive	e, selectable wit	th F39-U1E						
Connection method	For extension cable: 8 pins, M12 connector For series connection cable: 6 pins, M12 connector								
Ambient temperature	Operating: -10	°C +55°C (with	no icing or conde	ensation)					
Degree of protection	IP65 (IEC60529	9)							
Size (cross section)	30x40 mm								

 $^{^{\}star 1}~$ For detailed type names and optical specifications, see "Type Naming Rule"





Category 4 / 2 safety light curtain

The MS4800 and MS2800 family of safety light curtain provides simplicity in mounting, configuring, daily use and maintenance by providing a:

- Sensing distance up to 20 m for 30 mm resolution and 7 m for 14 mm resolution
- LED bar for easy alignment and diagnosis
- DIP-switch setup for blanking, muting and optical coding
- Category 4 / 2 sensor complying with EN 61496-1
- All-in-one M12 connection and mounting concept with robust housing
- Multicascadable up to 4 sets

Ordering information

MS2800 Safety Category 2											
Connection features											
Standard Standalone operation											
Master Series connection, muting		Stan	dard			Master			Slave		
Slave Series connection only											
		MS28	300S-			MS28	00FS-		MS2800F-		
Function Set											
Basic Interlock, restart, EDM, 2 optical channels, integrated alignment tool	Basic		Advanced		Basic Advanc		anced				
Advanced Muting, blanking (fixed/floating)											
	MS280	OS-EB-	MS280	IOS-EA-	MS280	0FS-EB-	MS280	OFS-EA-	MS28	00F-E-	
Resolution	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm	
14 mm finger protection											
30 mm hand protection	MS2800S-EB-	MS2800S-EB-	MS2800S-EA-				MS2800FS-EA-			MS2800F-E-	
Length	014-	030-	014-	030-	014-	030-	014-	030-	014-	030-	
240 mm 2120 mm in	280 1800	280 2120	280 1800	280 2120	280 1800	280 2120	280 1800	280 2120	240 1280	280 2120	
40 mm increments											

MS4800 Safety Category 4

in the same same same same same same same sam										
Connection features Standard Standalone operation										
Master Series connection, muting		Stan	ndard			Master			Slave	
Slave Series connection only										
		MS48	300S-			MS48	00FS-		MS48	300F-
Function Set										
Basic Interlock, restart, EDM, 2 optical channels, integrated alignment tool Advanced	Basic		Advanced		Basic		Advanced			
Muting, blanking (fixed/floating)										
	MS480	OS-EB-	MS480	OS-EA-	MS480	MS4800FS-EB- MS4800FS-EA-		OFS-EA-	MS48	00F-E-
Resolution	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm	14 mm	30 mm
14mm finger protection										
30mm hand protection	MS4800S-EB-	MS4800S-EB-	MS4800S-EA-					MS4800FS-EA-		MS4800F-E-
Length	014- 030-		014-	030-	014-	030-	014-	030-	014-	030-
240mm 2120mm in	280 1800	280 2120	280 1800	280 2120	280 1800	280 2120	280 1800	280 2120	240 1280	280 2120
40mm increments										

Examples

MS2800S-EB-030-1000

Standalone operation Basic function set 30 mm resolution 1000 mm protective height MS4800FS-EA-014-1200 Series connection model Advanced function set 14 mm resolution 1200 mm protective height MS4800F-E-014-600 Slave operation

14 mm resolution 600 mm protective height




Specifications

Model	MS4800E	MS2800E				
Sensor type	Type 4	Type 4 Type2				
Normal operating range Reduced range (DIP-switch 6)	14 mm resolution: 0.3 - 7 m, 30 mm resolution: 0.3 14 mm resolution: 0.3 - 3 m, 30 mm resolution: 0.3					
Beam pitch	14 mm resolution: 10 mm; 30 mm resolution: 20 mm	n				
Protective height	14 mm resolution: 280 - 1800 mm; 30 mm resolution	on: 240 - 2120 mm				
Detection capability	14 mm resolution: 14 mm non-transparent; 30 mm	resolution: 30 mm non-transparent				
Effective aperture angle (EAA)	Within ±2,5°	Within ±5,0°				
	for the emitter and receiver at a detection distance of	of at least 3m according to IEC61496-2				
Light source	Infrared LED's (880 nm), Power dissipation: 180 mW	/, Class 1 per EN60825-1				
Supply voltage (Vs)	24 VDC ±20%, according EN/IEC60204, able to cover	er a drop of voltage of at least 20 msec				
OSSD	Two safety related PNP transistor output, load current	Two safety related PNP transistor output, load current 625 mA max.*1, short circuit protection				
Auxiliary output (non safety output)	One PNP output sourcing 100 mA @ 24 VDC. This or	One PNP output sourcing 100 mA @ 24 VDC. This output follows the OSSD's				
Output operation mode	OSSD output: Light-ON	OSSD output: Light-ON				
Test functions	Self-test (after power ON and during operation)					
Safety-related functions	All versions: Auto reset/interlock with manual reset, floating blanking, muting	All versions: Auto reset/interlock with manual reset, EDM (external device monitoring) advanced versions only: fixed blanking, floating blanking, muting				
Response time	ON to OFF: 14 to 59 ms					
Ambient light intensity	Incandescent lamp: 3000 lx max. (light intensity on	the receiver surface)				
Ambient temperature	Operating: -10°C to +55°C, storage: -25°C to +70°C	C (without icing or condensation)				
Degree of protection	IP65 (IEC60529)					
Connection methode	Flexible cable with M 12 connection: receiver: 8 pins	s, transmitter: 5 pins				
Materials	Case: Polyurethane powder painted aluminium, cap:	polycarbonate, front window: acrylic, mounting brackets: cold rolled steel				
Size (cross section)	39 x 50 mm					
Receiver indicator lights	Individual Beam Indicator (IBI), interlock, blanking ac	ctiv, RUN and STOP state, error codes				
Transmitter indicator lights	ON, OFF, failure					
AOPD (ESPE)	Type4 acc. IEC 61496-1	Type2 acc. IEC 61496-1				
Suitable for safety control systems	Cat. 4 acc. EN954-1, PLe acc. EN ISO 13849-1	Cat. 4 acc. EN954-1, PLe acc. EN ISO 13849-1 Cat. 2 acc. EN954-1, PLc acc. EN ISO 13849-1				
Safety Integrity Level	SIL 3 according IEC 61508	SIL 3 according IEC 61508				
PFH	3,5 x 10 ⁻⁸	3,5 x 10 ⁻⁸				

 $^{^{\}star 1}$ Up to 12 m we recommend to use the F39-JMR cables, to use longer cables and a current of 625 mA the F39-JMR cables are necessary.

Connection example

Using a manual restart and an external device monitoring







Category-4 safety light curtain/ multi-beam safety sensor

The F3SN family is a category-4 safety light curtain with resolutions of 14, 25, 30 and 60 mm. An operating range of up to 10 m and protective heights from 189 to 1,822 mm are provided with no dead zone.

- Detection height = sensor length
- Sensing distance up to 7 m (14 mm resolution) and 10 m for all other types
- LED bar for easy alignment and diagnosis
- Blanking function by using setup console
- · Category-4 sensor complying with EN 61496-1

Ordering information

Safety light curtains

Minimum detection object	Sensing distance	Series connection, connector	Order code*1
14 mm dia. (finger protection)	0.2 to 7 m	No	F3SN-AP14 F3SN-AP14H
		Yes	F3SN-AP14H-01
25 mm dia.	0.2 to 10 m	No	F3SN-AP25
(hand protection)		Yes	F3SN-AP25-01
40 mm dia.	0.2 to 10 m	No	F3SN-AP40
(for presence protection)		Yes	F3SN-AP40-01
70 mm dia.	0.2 to 10 m	No	F3SN-AP70
(for presence detection)		Yes	F3SN-AP70-01

 $^{^{\}star 1}$ ____ in the model name indicates the detection width (mm).

List of safety light curtains

F3SN-A	P14.	F3SN-A	P14-01.	F3SN-A	P14H-01

Number of optical axes	Order code
23	F3SN-A0207P14 (-01)
33	F3SN-A0297P14 (-01)
45	F3SN-A0405P14 (-01)
55	F3SN-A0495P14 (-01)
67	F3SN-A0603P14 (-01)
79	F3SN-A0711P14 (-01)
89	F3SN-A0801P14 (-01)
101	F3SN-A0909P14 (-01)
111	F3SN-A0999P14 (-01)
123	F3SN-A1107P14 (-01)
133	F3SN-A1197P14H(-01)
151	F3SN-A1359P14H(-01)
167	F3SN-A1503P14H(-01)
179	F3SN-A1611P14H(-01)
	33 45 55 67 79 89 101 111 123 133 151

F3SN-A____P25, F3SN-A____P25-01

Detection height	Number of optical axes	Order code
307	19	F3SN-A0307P25 (-01)
457	29	F3SN-A0457P25 (-01)
607	39	F3SN-A0607P25 (-01)
907	59	F3SN-A0907P25 (-01)
1,057	69	F3SN-A1057P25 (-01)
1,207	79	F3SN-A1207P25 (-01)
1,357	89	F3SN-A1357P25 (-01)
1,507	99	F3SN-A1507P25 (-01)
1,657	109	F3SN-A1657P25 (-01)
1,807	119	F3SN-A1807P25 (-01)

Note: Highlighted products are preferred stock types, other detection heights are available.

Accessories (order separately)

Setting console

Order code	Accessories
F39-MC11	One branching connector, one connector cap, 2 m cable, instruction manual



Specifications


tem	Stand-alone	F3SN-A P14 *1 *3	F3SN-A P25 *1	F3SN-A P40 *1	F3SN-A P70 *1		
	Series connection	F3SN-A P14-01 *1 *2 *3	F3SN-A P25-01 *1	F3SN-A P40-01 *1	F3SN-A P70-01*1		
Sensor type		Type 4 Safety Light Curtain					
perating	g range	0.2 to 7 m	0.2 to 10 m				
Beam pitch (P) 9 mm 15 mm				30 mm	60 mm		
Protective	e height (PH)	189 to 1611 mm PH = n × P	217 to 1822 mm PH = (n - 1) × P + 37	217 to 1807 mm PH = $(n - 1) \times P + 37$	277 to 1777 mm PH = $(n - 1) \times P + 37$		
utermos	st beam gap	-					
			Non-transparent: 25 mm in diameter	Non-transparent: 40 mm in diameter	Non-transparent: 70 mm in diameter		
ffective	aperture angle (EAA)	Within ±2.5° for the emitter and rece	iver at a detection distance of at lea	st 3 m according to IEC 61496-2			
ight sou	rce	Infrared LED (870 nm)					
Supply vo	oltage (Vs)	24 VDC ±10% (ripple p-p 10% max.)					
SSD		Two PNP transistor outputs, load cur	rent 300 mA max.				
Auxiliary non-safe	output ety output)	One PNP transistor output, load curre	nt 50 mA max.				
xternal i non-safe	indicator output ety output) ^{*4}	One PNP transistor output, load current 40 mA max.					
Output op	peration mode	OSSD output: Light-ON Auxiliary output: Dark-ON (can be changed by the F39-MC11) External indicator output: Light-ON (can be changed by the F39-MC11) *4					
nput volt	tage	For test input, interlock selection input, reset input, and external relay monitor input voltages; ON voltage: 9 to 24 V (with a sink current of 3 mA max.), OFF voltage: 0 to 1.5 V or open					
Test func	tions	Self-test (after power ON, and during operation, one cycle during response time) External test (light emission stop function by test input)					
Safety-re	lated functions	Auto reset/manual reset (interlock) *5 EDM (external device monitoring) Fixed blanking *6 Floating blanking *6					
Response	e time	ON to OFF: 10 to 15.5 ms max., 19,5	ms max. for 179 beams				
Ambient I	light intensity	Incandescent lamp: 3000 lx max. (light intensity on the receiver surface) Sunlight: 10000 lx max. (light intensity on the receiver surface)					
mbient	temperature	Operating: -10°C +55°C, storage: -3	0°C +70°C (with no icing or condens	eation)			
egree of	f protection	IP65 (IEC60529)					
onnectio	on method	M12 connector (8 pins)					
/laterials		Case: Aluminum, cap: Zinc die-cast,	optical cover: PMMA (acrylic resin)				
Size (cros	ss section)	30x30 mm					


The 4 digits in ____ in the model number represent the protective height. Use the formula given in the information on protective height specifications to calculate the height. For example, if the beam gap is 9 mm, and the No. of beams is 21, the protective height will be 9×21 = 189 mm. The model with this protective height is F3SN-A0189P14. F3SN-A____P14-01 is a customized model. Consult with your Omron representative when ordering this model.

For sizes above 1,125 mm add "H" after P14, e.g. F3SN-A1143P14H. Ask for supplemental manual.

*4 Models ending in -01 only.

Connection





S2: Interlock/lockout reset switch
S3: Lock-out reset switch if the switch is not needed, connect to 24 VDC)
K1, K2: Relays for control of dangerous parts of machine.
K3: Load, PLC, etc. (for monitor)

Note: If you do not intend to use the external relay monitor, connect the auxiliary output that is set for dark: ON operation to the external relay monitor input, or use F39-MC11 to disable the external relay monitor function.

Models ending in -U1 only.
 For the factory setting, the manual reset mode is set to the "start/restart" interlock.
 Using the F39-MC11 can select either the start interlock or the restart interlock.
 For the factory setting, the function is not set. It can be enabled with the F39-MC11.



Multi-beam, finger- and hand protection safety sensor

The multi-beam sensors are available in Category 2 (PL c) and Category 4 (PL e) with integrated muting function. The finger- and hand protection models are available in Category 2 (PL c) and Category 4 (PL e) with integrated safety control functions.

- Type 2/Type 4 sensor complying with EN 61496-1
- · Family concept in wiring and mounting

Multi-beam models

- . Sensing distance up to 50 m
- DIP-switch setup for muting, pre-reset, interlock function and optical coding
- · Muting function and muting lamp integrated

Finger- and hand protection models

- Sensing distance up to 0.2 m...6 m (14 mm) and 0.2 m...14 m (35 mm)
- · DIP-switch setup for blanking, interlock function, muting and optical coding
- · Floating blanking and fixed blanking supported

Ordering information multi-beam safety sensors

Long-range active/active systems

F3S-TGR-CL2_-K_ (Type 2)

Number of optical axes	Sensing distance	Beam pitch	Feature set*1	Order code
2	0.5 m 40 m	500	Advanced	F3S-TGR-CL2A-K2-500
2	0.5 m 40 m	500	Basic	F3S-TGR-CL2B-K2-500
3	0.5 m 40 m	400	Advanced	F3S-TGR-CL2A-K3-800
3	0.5 m 40 m	400	Basic	F3S-TGR-CL2B-K3-800
4	0.5 m 40 m	300	Advanced	F3S-TGR-CL2A-K4-900
4	0.5 m 40 m	300	Basic	F3S-TGR-CL2B-K4-900
4	0.5 m 40 m	400	Advanced	F3S-TGR-CL2A-K4-1200
4	0.5 m 40 m	400	Basic	F3S-TGR-CL2B-K4-1200
2	25 m 50 m	500	Advanced	F3S-TGR-CL2A-K2-500-LD
2	25 m 50 m	500	Basic	F3S-TGR-CL2B-K2-500-LD
3	25 m 50 m	400	Advanced	F3S-TGR-CL2A-K3-800-LD
3	25 m 50 m	400	Basic	F3S-TGR-CL2B-K3-800-LD
4	25 m 50 m	300	Advanced	F3S-TGR-CL2A-K4-900-LD
4	25 m 50 m	300	Basic	F3S-TGR-CL2B-K4-900-LD
4	25 m 50 m	400	Advanced	F3S-TGR-CL2A-K4-1200-LD
4	25 m 50 m	400	Basic	F3S-TGR-CL2B-K4-1200-LD

F3S-TGR-CL4_-K_ (Type 4)

Number of	Sensing distance	Beam pitch	Feature set*1	Order code
optical axes				
2	0.5 m 40 m	500	Advanced	F3S-TGR-CL4A-K2-500
2	0.5 m 40 m	500	Basic	F3S-TGR-CL4B-K2-500
3	0.5 m 40 m	400	Advanced	F3S-TGR-CL4A-K3-800
3	0.5 m 40 m	400	Basic	F3S-TGR-CL4B-K3-800
4	0.5 m 40 m	300	Advanced	F3S-TGR-CL4A-K4-900
4	0.5 m 40 m	300	Basic	F3S-TGR-CL4B-K4-900
4	0.5 m 40 m	400	Advanced	F3S-TGR-CL4A-K4-1200
4	0.5 m 40 m	400	Basic	F3S-TGR-CL4B-K4-1200
2	25 m 50 m	500	Advanced	F3S-TGR-CL4A-K2-500-LD
2	25 m 50 m	500	Basic	F3S-TGR-CL4B-K2-500-LD
3	25 m 50 m	400	Advanced	F3S-TGR-CL4A-K3-800-LD
3	25 m 50 m	400	Basic	F3S-TGR-CL4B-K3-800-LD
4	25 m 50 m	300	Advanced	F3S-TGR-CL4A-K4-900-LD
4	25 m 50 m	300	Basic	F3S-TGR-CL4B-K4-900-LD
4	25 m 50 m	400	Advanced	F3S-TGR-CL4A-K4-1200-LD
4	25 m 50 m	400	Basic	F3S-TGR-CL4B-K4-1200-LD

Short-range active/passive systems

F3S-TGR-CL2_-K_C (Type 2)

Number of optical axes	Sensing distance	Beam pitch	Feature set*1	Order code
2	0.5 m 12 m	500	Advanced	F3S-TGR-CL2A-K2C-500
2	0.5 m 12 m	500	Basic	F3S-TGR-CL2B-K2C-500
3	0.5 m 8 m	400	Advanced	F3S-TGR-CL2A-K3C-800
3	0.5 m 8 m	400	Basic	F3S-TGR-CL2B-K3C-800
4	0.5 m 7 m	300	Advanced	F3S-TGR-CL2A-K4C-900
4	0.5 m 7 m	300	Basic	F3S-TGR-CL2B-K4C-900
4	0.5 m 7 m	400	Advanced	F3S-TGR-CL2A-K4C-1200
4	0.5 m 7 m	400	Basic	F3S-TGR-CL2B-K4C-1200

^{*1.} Feature set: Basic: Manual/automatic restart, coding Advanced: Basic + Muting + Pre-reset

F3S-TGR-CL4_-K_C (Type 4)

Number of optical axes	Sensing distance	Beam pitch	Feature set*1	Order code
2	0.5 m 12 m	500	Advanced	F3S-TGR-CL4A-K2C-500
2	0.5 m 12 m	500	Basic	F3S-TGR-CL4B-K2C-500
3	0.5 m 8 m	400	Advanced	F3S-TGR-CL4A-K3C-800
3	0.5 m 8 m	400	Basic	F3S-TGR-CL4B-K3C-800
4	0.5 m 7 m	300	Advanced	F3S-TGR-CL4A-K4C-900
4	0.5 m 7 m	300	Basic	F3S-TGR-CL4B-K4C-900
4	0.5 m 7 m	400	Advanced	F3S-TGR-CL4A-K4C-1200
4	0.5 m 7 m	400	Basic	F3S-TGR-CL4B-K4C-1200

Ordering information finger- and hand protection safety sensors

Safety category	Feature set*2	Resolution	Length	Order code
2	Basic	14 mm	150 mm2400 mm	F3S-TGR-CL2B-014-
		35 mm		F3S-TGR-CL2B-035-
	Advanced	14 mm		F3S-TGR-CL2A-014-
		35 mm		F3S-TGR-CL2A-035-
4	Basic	14 mm		F3S-TGR-CL4B-014-
		35 mm		F3S-TGR-CL4B-035-
	Advanced	14 mm		F3S-TGR-CL4A-014-
		35 mm		F3S-TGR-CL4A-035-

^{*2.} Feature set: Basic: Manual/automatic restart, coding Advanced: Blanking functions + muting + pre-reset



Specifications

Multi-beam safety sensors


Item	F3S-TGR-CL2K_		F3S-TGR-CL4K_		
Sensor Type	Type 2		Type 4		
Operating range	F3S-TGR-CLK_ F3S-TGR-CLKLD F3S-TGR-CLK2C-500 F3S-TGR-CLK3C-800 F3S-TGR-CLK4C	0.5 m 40 m 25 m 50 m 0.5 m 12 m 0.5 m 8 m 0.5 m 7 m			
Beam pitch	F3S-TGR-CLK2500: F3S-TGR-CLK3800: F3S-TGR-CLK4900: F3S-TGR-CLK41200:	2 beams, 500 mm 3 beams, 400 mm 4 beams, 300 mm 4 beams, 400 mm			
Effective aperture angle acc. EN 61496-2 (2006) for distances >3 m	Within ±5°		Within ±2.5°		
Light source	Infrared LED (880 nm), power di	issipation <3 mW, Class 1 per EN 60825-1			
Supply Voltage	24 VDC±20%, according EN/IEC	C60204 able to cover a drop of voltage of at least	20 ms		
OSSD	2 PNP transistor outputs, load c	2 PNP transistor outputs, load current 2x250 mA max			
Test functions	Self test (after power ON and du	ring operation)			
Safety-related functions	All versions: Auto reset/ interloc Advance version only: Muting ar	k with manual reset, EDM (external device monit nd pre-reset function	oring)		
Response time	< 13 ms				
Ambient temperature	Operating: -10°C+55°C, Stor	rage: -25°C+70°C (no icing, no condensation)			
Degree of protection	IP 65 (IEC 60529)				
Materials	Case: Painted aluminium, front window: Acrylic Lexan, Cap: ABS, mounting brackets: cold rolled steel				
Size (cross section)	37x48 mm				
Suitable for safety control systems	tems Cat. 2 (EN954-1), PLc (EN ISO 13849-1) Cat. 4 (EN954-1), PLe (EN ISO 13849-1)				
MTTFd, DC	MTTFd = 450 years, DC = high, MTTR = 8 hours				
PFH, Proof test interval	PFHd = 2,5*10 ⁻⁹ , Proof test interval: every 20 years				

Finger- and hand safety protection sensors

Item	F3S-TGR-CL20	F3S-TGR-CL40	
Sensor type	Type 2	Type 4	
Operating range: short setting	F3S-TGR-CL014: 0.2 m 3 m; F3S-TGR-CL035: 0.2 m 7 m		
Operating range: long setting	F3S-TGR-CL014: 3 m 6 m; F3S-TGR-CL035: 7 m14 m		
Beam pitch (center)	14 mm resolution: 7.5 mm 35 mm resolution: 18 mm		
Detection capability	14 mm resolution: 14 mm non-transparent 35 mm resolution: 35 mm non-transparent		
Effective aperture angle acc. EN 61496-2 (2006) for distances < 3 m	Within ±5°	Within ±2.5°	
Light source	Infrared LED (880 nm), power dissipation <3 mW, Class 1 per EN 60825-1		
Supply voltage	24 VDC±20%, according EN/IEC60204 able to cover a drop of voltage of at least 20 ms		
OSSD	2 PNP transistor outputs, load current 2x250 mA max		
Test functions	Self test (after power ON and during operation)		
Safety-related functions	All versions: Auto reset/ interlock with manual reset, EDM (external device monitoring) Advance version only: Blanking, muting and pre-reset function		
Response time	ON to OFF: 14 ms103 ms		
Ambient temperature	Operating: -10°C+55°C, Storage: -25°C+70°C (no icing, no condensation)		
Detgree of protection	IP 65 (IEC 60529)		
Materials	Case: Painted aluminium, Front window: Acrylic Lexan, Cap: ABS, mounting brackets: cold rolled steel		
Size (cross section)	37x48 mm		
Suitable for safety control systems	s Cat. 2 (EN954-1), PL c (EN ISO 13849-1) Cat. 4 (EN954-1), PL e (EN ISO 13849-1)		
MTTFd, DC	MTTFd = 450 years, DC = high, MTTR = 8 hours		
PFH, Proof test interval	PFHd = 2,5*10 ⁻⁹ , Proof test interval: every 20 years		




F3S-TGR-CL and GSB-301-D in manual reset



Standard cables

Receiver cables (M12-8pin, shielded, flying leads)				
F39-TGR-CVL-B-2-R	Receiver cable, 2 m length			
F39-TGR-CVL-B-5-R	Receiver cable, 5 m length			
F39-TGR-CVL-B-10-R	Receiver cable, 10 m length			
F39-TGR-CVL-B-15-R	Receiver cable, 15 m length			
F39-TGR-CVL-B-25-R	Receiver cable, 25 m length			
Transmitter cables (M12-4pin, shielded, flying leads)				
F39-TGR-CVL-B-2-E	Transmitter cable, 2 m length			
F39-TGR-CVL-B-5-E	Transmitter cable, 5 m length			
F39-TGR-CVL-B-10-E	Transmitter cable, 10 m length			
F39-TGR-CVL-B-15-E	Transmitter cable, 15 m length			
F39-TGR-CVL-B-25-E	Transmitter cable, 25 m length			

Mounting bracket F39-TGR-ST-ADJ



Wiring accessories (connectors and Y-connector cables)

Туре	
F39-TGR-CT-B-R	Connector M12, 8-pin, female for wiring
F39-TGR-CT-B-E	Connector M12, 4-pin, female for wiring
F39-TGR-CT-W-R	Connector M12, 8-pin, male for wiring
F39-TGR-CT-W-E	Connector M12, 4-pin, male for wiring
F39-TGR-CVL-D-B-5-R	Cable for sensor system and muting lamp connection


Safety relay units

Family	Type name	Configuration		
G9SB	G9SB-200-D	DPST-NO		
	G9SB-301-D	3PST-NO		
G9SA	G9SA-301	3PST-NO		
	G9SA-501	5PST-NO		
	G9SA-321-T075	3PST-NO, Time del. 7.5 s		
	G9SA-321-T15	3PST-NO, Time del. 15 s		
	G9SA-321-T30	3PST-NO, Time del. 30 s		
G9SX	G9SX-BC202-RT	2 Safe outputs		
	G9SX-BC202-RC	2 Safe outputs		
	G9SX-AD322-T15-RT	3 Safe outputs, Time del. 15 s		
	G9SX-AD322-T15-RC	3 Safe outputs, Time del. 15 s		
	G9SX-AD322-T150-RT	3 Safe outputs, Time del. 150 s		
	G9SX-AD322-T150-RC	3 Safe outputs, Time del. 150 s		
	G9SX-ADA222-T15-RT	2 Safe outputs, Time del. 15 s		
	G9SX-ADA222-T15-RC	2 Safe outputs, Time del. 15 s		
	G9SX-ADA222-T150-RT	2 Safe outputs, Time del. 150 s		
	G9SX-ADA222-T150-RC	2 Safe outputs, Time del. 150 s		
DeviceNet	NE1A-SCPU01	16 In, 8 Out, Safety master		
safety	NE1A-SCPU02	40 In, 8 Out, Safety master		
Safety	NE1A-SCPU01L	16 In, 8 Out		
controller	NE1A-SCPU02L	40 In, 8 Out		
Relay interface	F39-TGR-SB-R	Relay interface for semiconductor OSSDs		




F3S-TGR-CL Safety sensors

Dimensions



- L: Total length of the F3S-TGR-CL system
- F: Protective height where an object equal or greater the resolution is detected
- E: Detection zone
- A: Dead zone without detection capability

Alternate T-slot mounting



F3S-TGR-CL system data with 14 mm resolution

Model number	150	300	450	600	750	900	1050	1200	1350	1500	1650	1800	1950	2100	2250	2400
L [mm]	217	364	511	658	805	952	1099	1246	1393	1540	1687	1834	1981	2128	2275	2422
F [mm]	161	308	455	602	749	896	1043	1190	1337	1484	1631	1778	1925	2072	2219	2366
A [mm]	59	59	59	59	59	59	59	59	59	59	59	59	59	59	59	59
Weight [kg]	0.83 kg	1.39 kg	1.95 kg	2.51 kg	3.07 kg	3.63 kg	4.19 kg	4.75 kg	5.31 kg	5.87 kg	6.43 kg	7 kg	7.55 kg	8.11 kg	8.67 kg	9.24 kg

F3S-TGR-CL system data with 35 mm resolution

Model number	150	300	450	600	750	900	1050	1200	1350	1500	1650	1800	1950	2100	2250	2400
L [mm]	217	364	511	658	805	952	1099	1246	1393	1540	1687	1834	1981	2128	2275	2422
F [mm]	182	329	476	623	770	917	1064	1211	1358	1505	1652	1799	1946	2093	2240	2387
A [mm]	59	59	59	59	59	59	59	59	59	59	59	59	59	59	59	59
Weight [kg]	0.83 kg	1.39 kg	1.95 kg	2.51 kg	3.07 kg	3.63 kg	4.19 kg	4.75 kg	5.31 kg	5.87 kg	6.43 kg	7 kg	7.55 kg	8.11 kg	8.67 kg	9.24 kg

F3S-TGR-CL-K system data

Model number	Weight	Dimensions				
		F [mm]	L [mm]	E [mm]	A [mm]	
F3S-TGR-CLK2C-500	2.3 kg	518	682	500	59	
F3S-TGR-CLK3C-800	3.2 kg	818	982	400	59	
F3S-TGR-CLK4C-900	4.1 kg	918	1082	300	59	
F3S-TGR-CLK4C-1200	4.9 kg	1218	1382	400	59	
F3S-TGR-CLK2-500	2.3 kg	518	682	500	59	
F3S-TGR-CLK3-800	3.2 kg	818	982	400	59	
F3S-TGR-CLK4-900	4.1 kg	918	1082	300	59	
F3S-TGR-CLK4-1200	4.9 kg	1218	1382	400	59	
F3S-TGR-CLK2-500-LD	2.3 kg	518	682	500	59	
F3S-TGR-CLK3-800-LD	3.2 kg	818	982	400	59	
F3S-TGR-CLK4-900-LD	4.1 kg	918	1082	300	59	
F3S-TGR-CLK4-1200-LD	4.9 kg	1218	1382	400	59	





OS32C Safety Laser Scanner

- Type 3 Safety laser scanner complies with IEC61496-1/-3.
- 70 sets of safety zone and warning zone combinations are available, supporting complicated changes in working environments.
- A safety radius up to 3 m and warning zone(s) radius up to 10 m can be set.
- 8 Individual sector indicators and various LED indications allow the user to determine scanner status at a glance.
- Reference boundary monitoring function prevents unauthorized changes in the scanner position.

Ordering information

OS32C (Power cable is sold separately.)

Description	Order code
Back location cable entry	OS32C-BP
Side location cable entry*1	0S32C-SP1

 $^{^{\}star 1}$ For OS32C-SP1, each connector is located on the left as viewed from the back of the I/O block.

Description	Remarks	Order code
Configuration tool	CD-ROM OS supported: Windows 2000; Windows XP; Windows Vista	included

Note: The OS32C laser scanner may not be sold or imported into or used in the Federal Republic of Germany prior to December 1, 2013.

Mounting brackets

Туре	Remarks	Order code
Bottom/side mounting bracket	Bottom/side mounting bracket x 1, unit mounting screws x 4 sets	0S32C-BKT1
XY axis rotation mounting bracket	XY axis rotation mounting bracket x 1, unit mounting screws x 6 sets, bracket mounting screws x 1 set (must be used with 0S32C-BKT1)	OS32C-BKT2

Note: For a full line-up of accessories and spare parts, please refer to the Z298-E1... datasheet.

Specifications

Sensors						
Sensor ty	уре	Type 3 Safety laser scanner				
Safety ca	ntegory	Category 3, performance level d (ISO13849-1: 2006)				
Detection	n capability	Non-transparent with a diameter of 70 mm (1.8% reflectivity or greater)				
Monitorii	ng zone	Monitoring zone set count: (Safety zone + 2 warning zones) x 70 sets				
Operatin	g range	Safety zone radius up to 3 m, warning zone radius up to 10 m.				
Detection	n angle	270°				
Respons	e time	Response time from ON to OFF: From 80 ms (2 scans) to 680 ms (up to 17 scans) Response time from OFF to ON: Response time from ON to OFF + 100 ms to 60 s (configurable)				
Line volt	age	24 VDC +25%/-30% (ripple p-p 2.5 V max.)*1				
Power consumption		Normal operation: 5 W max., 4 W typical (without output load) ^{*2} Standby mode: 3.75 W (without output load)				
Safety output (OSSD)		PNP transistor x 2, load current of 250mA max., residual voltage of 2 V max., load capacity of 2.2 µf max., leak current of 1 mA max. 2.73,*4				
Auxiliary output (Non-Safety)		NPN/PNP transistor x 1, load current of 100 mA max., residual voltage of 2 V max., leak current of 1 mA max. "3,"4,"5				
Warning output (Non-Safety)		NPN/PNP transistor x 1, load current of 100 mA max., residual voltage of 2 V max., leak current of 1 mA max.*3.*4,*5				
Output o	peration mode	Auto start, start interlock, start/restart interlock				
Input	External Device Monitoring (EDM)	ON: 0 V short (input current of 50 mA), OFF: Open				
	Start	ON: 0 V short (input current of 20 mA), OFF: Open				
	Zone select	ON: 24 V short (input current of 5 mA), OFF: Open				
	Stand-by	ON: 24 V short (input current of 5 mA), OFF: Open				
Connecti	on type	Power cable: 18-pin mini-connector (pigtail) Communication cable: M12, 4-pin connector				
Connecti	on with PC	Communication: Ethernet				
Indicators		RUN indicator: Green, STOP indicator: Red, Interlock indicator: Yellow, Warning output indicator: Orange, Status/diagnostic display: 2 x 7-segment LEDs, Intrusion indicators: Red LED x 8				
Enclosure rating		IP65 (IEC60529)				
Dimensio	ons (WxHxD)	133.0 x 104.5 x 142.7 mm (except cable)				
Weight (Main Unit only)	1.3 kg				
Approval	s	EN61496-1 (Type 3 ESPE), EN61496-3 (Type 3 AOPDDR), EN61508 (SIL2), IS013849-1 (Category 3, Performance Level d), UL508, UL1998, CAN/CSA-C22.2 No. 14, CAN/CSA-C22.2 No. 0.8				

For power source specification, refer to "Safety Precautions" on page 16.

^{*5} Output polarity (NPN/PNP) is configurable via the configuration tool.




Rated current of OS32C is 1.025 A max. (0S32C 210 mA + OSSD A load + OSSD B load + auxiliary output load + warning output load + functional Inputs). Where functional inputs are: EDM input ... 50 mA Start input ... 20 mA Standby input ... 5 mA Zone X input ... 5 mA x 8 (eight zone set select inputs) Output voltage is input voltage - 2.0 VDC.

Total consumption current of 2 OSSDs, auxiliary output, and warning output must not exceed 700 mA.


Connection

Basic connection with single OS32C unit Category 3, performance level d (ISO13849-1)




Dimensions

OS32C with back location cable entry - OS32C-BP



OS32C with side Llcation cable entry - OS32C-SP1





Single-beam safety sensor in compact housing

The slender M18-sized E3FS is a type 2 safety single beam with an operating range of up to 10 m. Plastic and metal housing, cable and M12-connector offer flexibility in application together with a control unit such as F3SP-U3P or F3SP-U5P.

- Sensing distance up to 10 m
- LEDs for easy alignment and diagnosis
- Cable and M12 plug categories
- · Plastic and metal housing
- Type 2 sensor complying with EN 61496-1

Ordering information

Safety single beam sensors (Type 2)						
Case material	Operation distance	Order code				
Plastic	0 to 10 m	Cable type	E3FS-10B4			
		Plug type	E3FS-10B4-P1			
Nickel brass		Cable type	E3FS-10B4-M			
		Plug type	E3FS-10B4-M1-M			

Controller for safety single beam sensors						
Sensors	Output contacts	Width	Order code			
1 to 2 Safety single beam sensors	2 NO 2.5 A	22.5 mm	F3SP-U3P-TGR			
1 to 4 Safety single beam sensors		45 mm	F3SP-U5P-TGR			

Specifications

Sensors	
Sensing method	Through-beam
Controller	F3SP-U3P-TGR, F3SP-U5P-TGR
Supply voltage (Vs)	24 VDC ± 10% (ripple p-p 10% max.)
Effective aperture angle (EAA)	±5° (at 3 m)
Current consumption	Emitter: 50 mA max. Receiver: 25 mA max.
Sensing distance	10 m
Standard sensing object	Opaque object: 11 mm min. in diameter
Response time	2.0 ms (E3FS only)
Control output	PNP transistor output, load current: 100 mA max.
Test input (emitter)	21.5 to 24 VDC: Emitter OFF (source current: 3 mA max.) Open or 0 to 2.5 V: Emitter ON (leakage current: 0.1 mA max.)
Ambient light intensity	Incandescent lamp: 3.000 lx max. (light intensity on the receiver surface) Sunlight: 10,000 lx max. (light intensity on the receiver surface)
Ambient temperature	Operating: -20°C +55°C, storage: -30°C +70°C (with no icing or condensation)
Degree of protection	IP67 (IEC 60529)
Light source	Infrared LED
Protection	Output short-circuit protection, reverse polarity protection
0	

Controllers

OUTHORETS		
Item	F3SP-U3P	F3SP-U5P
Number of sensors	1 to 2 safety single beam sensor	1 to 4 safety single beam sensor
Width	22.5 mm	45 mm
Muting input	2 Inputs	4 Inputs
Safety related function	Override function Muting lamp connection Interlock system (automatic and manual reset)	
Power supply voltage	24 VDC ±10%	
Power consumption	420 mA max.	
Output contacts	2 NO 2.5 A (protected by fuse), 115 VAC max.	2 NO 2.5 A (protected by fuse), 250 VAC max.
Indicators	6 LED for status and diagnostics	
Degree of protection	IP20 (IEC 60529)	
Terminal	16 screw terminals, detachable blocks with '4pin'	32 screw terminals, detachable blocks with '4pin'
Response time	≤ 30 ms	
Ambient temperature	Operation: -10°C +55°C	
Housing material	Plastic; DIN rail mounting	





Safety light curtain controller with integrated muting function

The F3SP-U4P muting controller can handle up to two safety light curtains. It has a 45 mm-wide housing, two safety relay outputs with up to 2.5 A and additional functions such as muting-lamp monitoring and override function.

- Two independent muting functions with override
- Slim housing: 45 mm
- · LEDs for status and diagnosis
- Detachable terminals
- Fully certified according to EN 61496-1

Ordering information


Description	Order code
Muting controller for safety light curtain F3S-B, F3SN and F3SH	F3SP-U4P-TGR

Specifications

Item	F3SP-U4P-TGR	
Power supply voltage	24 VDC ±10%	
Power consumption	420 mA max. (excl. SLC power consumption)	
Output contacts	at contacts 2 NO 2.5 A (protected by fuse)	
Indicators	6 LEDs for status and diagnostics.	
Degree of protection	IP20 (IEC 60529)	
Terminal	32 screw terminals (1.5 mm²), detachable blocks with 4 screws each	
Response time	me ≤ 30 ms	
Ambient temperature	Operating: -10 °C + 55 °C	
Housing material	Plastic, DIN rail mounting	

Wiring example

Control unit F3SP-U4P-TGR in a mixed configuration that allows the use of several Omron safety light curtains and perimetrical guards.






BREAK THROUGH BARRIERS IN SAFETY DESIGN


Configurable, flexible and simple

Omron safety controllers offer transparent standalone operation and scalability in safety networking applications for all sizes of machine safety control systems. The G9SP safety controller is simple to configure and setup and overcomes limitations of hard-wired solutions by adding flexibility of a software - based solution. Total cost of ownership is reduced by having user-defined function blocks and an integrated simulation tool for debugging or the application program.

- EN ISO 13849-1 (PLe) and IEC 61508 (SIL3) certification for future-proof design of the safety system
- · Predefined function blocks for simple configuration and self-explanatory validation
- · Equipped with Ethernet and serial interface for transparent diagnosis







Selection table

	Safety relay units Flexible safety unit Safety relays						
	Model	G9SA	G9SB	G9SX	G7SA		
	Safety category (EN 954-1)				-		
	Safety integrity level (IEC 61508)		- max. 10 ms	SIL 3	-		
	Reaction time DeviceNet safety	max. 10 ms	max. 10 ms	15 ms	-		
Selection criteria	Bus interface Standard DeviceNet Bus		-	-	_		
n Cri	interface						
ctio	EDM function				-		
Sele	Interlock function				-		
	Logical 'AND' connection		-	-	-		
	Relay expansion units Housing		- Plastic	Plastic	- Plastic		
	Operating temperature		-25 to +55°C	-10 to +55°C	-40 to +85°C		
	Flux-tight		-23 to +33 to	-10 to +35 C	-40 to +65 t		
	Number of poles		-	-	4pole and 6pole		
	Gold clad contacts		-	-			
	Relay socket	-	-	-			
Features	Detachable cage clamp terminals		-		-		
Feat	Screw terminals			_	-		
	Safe timing functions		_	-	-		
	USB-interface Programming software		-	-	-		
	E-Stop application		•		_		
	Door switch monitoring		-	_ _	-		
	Safety light curtain monitoring				-		
	EDM monitoring				-		
	Interlock function				-		
	Logic function blocks		-	-	-		
ie ie	Safe ON delay timer Safe OFF delay timer		-	-	-		
plication	Two-Hand control		_	-	_		
Арр	Manual/ automatic reset		•	•	-		
	Non-contact switches monitoring		-	•	-		
	Guard switching/ enabling function		-		-		
	limited speed monitoring		-	•	-		
	standstill monitoring General safety application		-		-		
ply age	24 VDC		•	•	•		
Supply voltage	100 VAC to 240 VAC		-	-	-		
	Safety inputs				-		
	Test signal output		-	-	-		
ats	Solid state safety outputs Safety relay outputs		DPST-NO, 3PST-NO	•	_		
outp	Auxiliary outputs		SPST-NC		-		
In- and outputs	4PST-NO + DPST-NC		-	-			
≟	3PST-NO + 3PST-NC		-	-			
	3PST-NO + SPST-NC		-	-			
	DPST-NO + DPST-NC		-	-			
	5PST-NO + SPST-NC		-	-			
	Page	3/9	378	384	393		



Safety control systems

		Programmable safety system					
	Model	COST	NEA CONIO I	NICA CONIO	TO THE STATE OF TH		
	Model Safety category (EN 954-1)	G9SP up to Category 4	NE1A-SCPUO_L	NE1A-SCPUO_	DST1		
	Safety integrity level (IEC 61508)						
	Reaction time						
ria	DeviceNet safety Bus interface	_	_				
Selection criteria	Standard DeviceNet Bus interface	Diagnosis via Ethernet and Serial interface (option)	•		•		
ecti	EDM function		_	_	_		
Sel	Interlock function		•		-		
	Logical 'AND' connection		-	-	-		
	Relay expansion units		- Diactic	- Diactic	- Diactic		
	Housing Operating temperature		Plastic -10 to +55°C	Plastic -10 to +55°C	Plastic -10 to +55°C		
	Flux-tight		-10 10 +55 0	-10 10 +55 * C	-10 10 +55 0		
	Number of poles		-	-	-		
	Gold clad contacts		-	-	-		
	Relay socket		-	-	-		
Features	Detachable cage clamp terminals	-	-		•		
eatn	Screw terminals		-	-	-		
ŭ	Safe timing functions						
	USB-interface				-		
	Programming software				-		
	E-Stop application		-				
	Door switch monitoring				•		
	Safety light curtain monitoring		•				
	EDM monitoring		-	-	_		
	Interlock function Logic function blocks		-	-	_		
	Safe ON delay timer		-	=	_		
io	Safe OFF delay timer		-	-	-		
plication	Two-Hand control		-	•	•		
App	Manual/ automatic reset		•	•	•		
	Non-contact switches monitoring						
	Guard switching/ enabling function		•	•			
	limited speed monitoring		-	-			
	standstill monitoring		-	-			
Supply voltage	General safety application 24 VDC		•	•			
	100 VAC to 240 VAC	-	-	-	-		
	Safety inputs			•			
	Test signal output						
In- and outputs	Solid state safety outputs		•	•			
	Safety relay outputs		-	_			
	Auxiliary outputs		•				
	4PST-NO + DPST-NC 3PST-NO + 3PST-NC		-	-	-		
	3PST-NO + 3PST-NC		-	-	-		
	DPST-NO + DPST-NC		-	-	-		
	5PST-NO + SPST-NC		-	-	-		
	Page		390		391		

■ Standard

No/not available





Slim-size safety unit

G9SB is a family of slender safety relay units, providing two safety contacts in a 17.5 mm- and three safety contacts in a 22.5mm-wide housing.

- 17.5 mm- and 22.5 mm-wide housing
- 1- and 2-input channel units
- Manual and automatic reset units
- Certification up to category 4 according to EN954-1 depending on the application

G9SB-301_-_

Ordering information

Main contacts	Auxiliary contact	Number of input channels	Reset mode	Input type	Rated voltage	Category (EN954-1)	Size	Order code
DPST-NO	None	2 channels	Auto-reset	Inverse	24 VAC/VDC	4	17.5 mm	G9SB-2002-A
2 safety contacts		1 channel or 2 channels		+ common				G9SB-200-B
		2 channels	Manual-reset	Inverse				G9SB-2002-C
		1 channel or 2 channels		+ common				G9SB-200-D
3PST-NO 3 safety	SPST-NC	None (direct breaking)	Auto-reset	-	24 VDC	3	17.5 mm	G9SB-3010
contacts		2 channels		Inverse	24 VAC/VDC 4	4	22.5 mm	G9SB-3012-A
		1 channel or 2 channels		+ common				G9SB-301-B
		2 channels	Manual-reset	Inverse				G9SB-3012-C
		1 channel or 2 channels		+ common				G9SB-301-D

Specifications

Power input			
Item	G9SB-200	G9SB-3010	G9SB-301
Power supply voltage	24 VAC/VDC: 24 VAC, 50/60 Hz, or 24VDC 24 VDC: 24 VDC		
Operating voltage range	85 to 110% of rated power supply voltage		
Power consumption	1.4 VA/1.4 W max. 1.7 VA/1.7 W max. 1.7 VA/1.7 W max.		
Inputs			
Item	G9SB-200	G9SB-3010	G9SB-301
Input current	25 mA max.	60 mA max. (See note.)	30 mA max.

Note: Indicates the current between terminals A1 and A2.

Contacts Item

		Resistive load (cosφ= 1)				
Rated load		250 VAC, 5 A				
Rated carry current		5 A				
Characteristics						
Item		G9SB-200	G9SB-3010	G9SB-301		
Response time *1		10 ms max.				
Durability Mechanical		5,000,000 operations min. (at approx. 7,200 operations/hr)				
Electrical		100,000 operations min. (at approx. 1,800 operations/hr)				
Minimum permissable load (reference value)		5 VDC, 1 mA				
Ambient operating temperature		-25°C +55°C (with no icing or condensation)				

G9SB-3010

G9SB-200_-_



 $^{^{\}star 1}$ The response time is the time it takes for the main contact to open after the input is turned OFF.



Expandable safety relay unit

G9SA-family offers a complete line-up of compact and expandable safety relay units. Modules with safe OFF-delay timing are available as well as a two-hand controller. Simple multiplication of safety contacts is possible by using the connection on the front.

- 45 mm-wide housing, expansion units are 17.5 mm wide
- · Safe OFF-delay timer
- · Simple expansion connection
- Certification up to category 4 according to EN954-1 depending on the application

Ordering information

Emerge	ency	-stop	units

Main contacts	Auxiliary contact	Number of input channels	Rated voltage	Category	Order code
3PST-N0	SPST-NC	1 channel or 2 channels possible	24 VAC/VDC	4	G9SA-301
			100 to 240 VAC		
5PST-NO	SPST-NC	1 channel or 2 channels possible	24 VAC/VDC		G9SA-501
			100 to 240 VAC		

Emergency-stop OFF-delay units

Main contacts	OFF-delay contacts	Auxiliary contact	Number of input channels	OFF-delay time	Rated voltage	Category	Order code
3PST-N0	DPST-NO	SPST-NC	1 channel or	1 channel or 7.5 s 24	24 VAC/VDC	Main contacts: 4	G9SA-321-T075
				100 to 240 VAC	OFF-delay contacts: 3		
		15 s	24 VAC/VDC		G9SA-321-T15		
			100 to 240 VAC				
			24 VAC/VDC		G9SA-321-T30		
			100 to 240 VAC				

Two-hand controller

Main contacts	Auxiliary contact	Number of input channels	Rated voltage	Category	Order code
3PST-NO	PST-NO SPST-NC 2 channels	24 VAC/VDC	4 (IIIc, EN574)	G9SA-TH301	
			100 to 240 VAC		

Expansion unit

The expansion unit connects to a G9SA-301, G9SA-501, G9SA-321, or G9SA-TH301.

Main contacts	Auxiliary contact	Category	Order code
3PST-N0	SPST-NC	4	G9SA-EX301

Expansion units with OFF-delay outputs

The expansion unit connects to a G9SA-301, G9SA-501, G9SA-321, or G9SA-TH301.

	Main contact form	Auxiliary contact	OFF-delay time	Category	Order code
	3PST-NO SPST-NO	SPST-NC	7.5 s	3	G9SA-EX031-T075
			15 s		G9SA-EX031-T15
			30 s		G9SA-EX031-T30

Specifications

Power input				
Item	G9SA-301/TH301 / G9SA-501 / G9SA-321-T_			
Power supply voltage	24 VAC/VDC: 24 VAC, 50/60 Hz, or 24 VDC 100 to 240 VAC:100 to 240 VAC, 50/60 Hz			
Operating voltage range	85 to 110% of rated power supply voltage			

Inputs		
Item	G9SA-301/321-T_/TH301	G9SA-501

Input current Contacts

oontaota	
Item	G9SA-301/501/321-T_/TH301/EX301/EX031-T_
	Resistive load (cos
Rated load	250 VAC, 5 A
Rated carry current	5 A

40 mA max.

60 mA max.

Characteristics

Item		G9SA-301/TH301 / G9SA-501/321-T_ / G9SA-EX301/EX031-T_				
Operating time		30 ms max. (not including bounce time)				
Response time *1		10 ms max. (not including bounce time)				
Durability Mechanical		5,000,000 operations min. (at approx. 7,200 operations/hr)				
Electrical		100,000 operations min. (at approx. 1,800 operations/hr)				
Minimum permissible load (reference value)		5 VDC, 1 mA				
Ambient temperature		Operating: -25 to 55°C (with no icing or condensation) Storage: -25 to 85°C (with no icing or condensation)				

 $^{^{\}star 1}$ The response time is the time it takes for the main contact to open after the input is turned OFF.





Compact non-contact door switch/ flexible safety unit

Electronic detection mechanism for better stability in non-contact door switch operation

- Stable operation reduces controller errors caused by unstable doors.
- Connect up to 30 non-contact door switches with LED indicators to one controller.
- · Reversible switch provides flexibility in installation.
- Two-color LED indicator enables easier maintenance by identification of door status and cable disconnections.
- Safety category 3 (EN 954-1).

Ordering information

Non-contact door switches (switch/actuator)

Classification	Auxiliary outputs	Cable length	Order code
Standard models	Semiconductor outputs *1	2 m	D40A-1C2
		5 m	D40A-1C5

^{*1} PNP open-collector semiconductor output.

Note: Must be used in combination with a G9SX-NS_ non-contactdoor switch controller.

On-contact door switch controllers (Controllers for D40A)

Safety outputs *1			Logical AND Logical Al	Logical AND		Rated	Terminal block type	Order code
Instantaneous	OFF-delayed *4	outputs *2	connection input	connection output	delay time ^{*3}	voltage		
2 (Semi-	0	2 (Semi-	1	1	_	24 VDC	Screw terminals	G9SX-NS202-RT
conductors)		conductors)					Spring-cage terminals	G9SX-NS202-RC
	2 (Semi-		3.0 s				Screw terminals	G9SX-NSA222-T03-RT
	conductors)						Spring-cage terminals	G9SX-NSA222-T03-RC

^{*1} P channel MOS FET transistor output

Specifications

Ratings/characteristics of non-contact door switches

Item	Model	D40A-1C_				
Operating characteristics *1	Operating distance OFF→ON	5 mm min.				
	Operating distance ON→OFF	15 mm max.				
	Differential travel (max.)	20% of operating distance				
Ambient operating temp	perature	-10 to 55°C (no icing or condensation)				
Vibration resistance		10 to 55 to 10 Hz (single amplitude: 0.75 mm, double amplitude: 1.5 mm)				
Shock resistance		300 m/s ² min.				
Degree of protection		IP67				
Material		PBT resin				
Mounting method		M4 screws				
Power consumption		0.6 W max.				
Auxiliary outputs *2		24 VDC, 10 mA (PNP open-collector outputs)				
LED indicators		Actuator not detected (red); actuator detected (yellow)				
Connection cables		2 m, 5 m				
Number of connectable	switches	30 max. (wiring length: 100 m max.)				

^{*1} This is the distance where the switch operates from OFF to ON when approaching and the distance where the switch operates from ON to OFF when separating when the switch and actuator target marks are on the same axis, and the sensing surfaces coincide.



^{*2} PNP transistor output

The OFF-delay time can be set in 16 steps as follows: 0/0.2/0.3/0.4/0.5/0.6/0.7/0.8/0.9/1.0/1.2/1.4/1.8/2.0/2.5/3.0 s

The OFF-delayed output becomes an instantaneous output by setting the OFF-delay time to 0 s.

^{*2} Turns ON when the actuator is approaching.

D40A/G9SX-NS

Ratings of non-contact door switch controllers

Power input


Item	G9SX-NS202	G9SX-NSA222-T03	G9SX-EX
Rated supply voltage	24 VDC		
Inputs			
Item	G9SX-NS202/G9SX-NSA222-T03		
Safety input *1	Operating voltage: 20.4 VDC to 26.4 VDC,	internal impedance: approx. 2.8 $k\Omega$	
Feedback/reset input			

 $^{^{\}star1}$ Only applies to the G9SX-NSA222-T03-_. Refers to input other than that from the non-contact door switch.

Outputs


Item	G9SX-NS202/G9SX-NSA222-T03
Instantaneous safety output OFF-delayed safety output	P channel MOS FET transistor output Load current: 0.8 A DC max.
Auxiliary output	PNP transistor output Load current: 100 mA max.

Non-contact door switch and non-contact door switch controller wiring Example: Wiring a single switch



Note: The auxiliary output load current must be 10 mA max.

Example: Wiring multiple switches Connect up to 30 Non-contact door switches







Safety guard switchting unit

The safety controller to support maintenance mode of machinery in the safe way.

• Two operation modes to support:

G9SX-EX-

- Auto switching for applications where machine and worker co-operate.
- Manual switching for applications with limitation in operation like maintenance.
- Clear and transparent segmentation of safety functions by use of unique "AND"connection
- Clear LED diagnosis of all in- and output signals for easy maintenance
- Category 4 according to EN954-1 and SIL 3 according to EN 61508.

Ordering information

Enabling	arip	switches

Contact form			Order code
Enabling switch	Monitor switch	Pushbutton switch	
Two contacts	1NC (grip output)	None	A4EG-C000041
Two contacts	None	Emergency stop switch (2NC)	A4EG-BE2R041
Two contacts	None	Momentary operation switch (2NO)	A4EG-BM2B041

Safety guard switching units

Safety outputs *1		Auxiliary	Logical AND	Logical AND	Max. OFF	Rated	Terminal block type	Order code
Instantaneous	OFF-delayed *4	outputs "2	connection input	connection output	delay time ³	voltage		
2 (Semi-	2 (Semi-	6 (Semi-	1	1	15 s	24 VDC	Screw terminals	G9SX-GS226-T15-RT
conductors)	conductors)	conductors)					Spring-cage terminals	G9SX-GS226-T15-RC

^{*1} P channel MOS FET transistor output

G9SX-GS226-T15-

Specifications

Ratings of non-contact door switch controllers

Power input

Item

Rated supply voltage	24 VDC
Inputs	
Item	G9SX-GS226-T15
Safety input	Operating voltage: 20.4 VDC to 26.4 VDC, internal impedance: approx. 2.8 $k\Omega$
Feedback/reset input	
Mode selector input	
Outputs	
Item	G9SX-G9SX-GS226-T15
Instantaneous safety output OFF-delayed safety output	P channel MOS FET transistor output Load current: 0.8 A DC max.
Auxiliary output	PNP transistor output Load current: 100 mA max.
External indicator outputs	P channel MOS FET transistor outputs Connectable indicators



^{**}Profilation with the translation of the translati


Application example

Automatic switching mode

Worker is loading and unloading the machine manually. When loading is finished, robot cycle is started manually by the worker. When robots return to their home position, loading cycle is selected automatically.

Loading condition: Safety sensor B is not active, safety sensor A is active because the robots are not allowed to move to the loading area while the worker loads the machine. So the worker is safe because safety sensor A is active.

Robot work condition: Safety sensor B is active, safety sensor A is not active because the worker is not allowed to move to the loading area when the robots work. So the worker is safe because safety sensor B stops the machine if he moves to the loading area.



Manual switching mode


Worker has to do maintenance in this machine. While maintenance, it is necessary to move the machine in a limited way. The worker has to select automatic mode or manual mode manually by using the mode selector switch.

Operation steps:

- 1) Select maintenance mode by using the mode selector
- Open the door to do the maintenance while the machine still is able to operate in a limited way (monitoring of limited movement by using the safety limit switch).
- 3) Close the cover after finishing maintenance
- 4) Select automatic mode by using the mode selector

E-Stop conditions:

- a) open the door while not in maintenance mode
- b) the machine actuates the limit switch (breaks the limit).
- c) the Enabling grip switch A4EG is actuated to stop the machine in emergency condition.





Flexible safety unit

G9SX-family modules can be connected by a logical "AND" function to implement partial/global stopping of a machine. Solid-state outputs, detailed LED diagnosis and clever feedback signals help to keep maintenance easy. The line-up is completed by expansion units with safe timing functions.

- Clear and transparent segmentation of safety functions by use of unique "AND" connection
- Solid-state outputs for long life and relay outputs in extension box available
- · Detailed LED indications enable easy diagnosis
- · Clever feedback signals for easy maintenance
- Category-4 according to EN954-1 and SIL 3 according to EN 61508

Ordering information

Advanced unit							
Safety outputs		Auxiliary outputs	No. of input	Max. OFF-delay	Rated	Terminal block type	Order code
Instantaneous	OFF-delayed		channels	time *1	voltage		
3 P channel MOS-FET	2 P channel MOS-FET	2 PNP transistor	1 or 2 channels	0 to 15 sec in	24 VDC	Screw terminals	G9SX-AD322-T15-RT
transistor output transistor output		outputs		16 steps		Cage clamp terminals	G9SX-AD322-T15-RC
2 P channel MOS-FET	2 P channel MOS-FET transistor output	T 2 PNP transistor outputs	1 or 2 channels	0 to 150 sec in 16 steps	24 VDC	Screw terminals	G9SX-AD-322-T150-RT
transistor output						Cage clamp terminals	G9SX-AD-322-T150-RC
				0 to 15 sec in 16 steps		Screw terminals	G9SX-ADA-222-T15-RT
						Cage clamp terminals	G9SX-ADA-222-T15-RC
				0 to 150 sec in 16 steps	24 VDC	Screw terminals	G9SX-ADA-222-T150-RT
						Cage clamp terminals	G9SX-ADA-222-T150-RC

^{*1} The OFF-delay time can be set in 16 steps as follows: T15: 0/0.2/0.3/0.4/0.5/0.6/0.7/1/1.5/2/3/4/5/7/10/15 s, T150: 0/10/20/30/40/50/60/70/80/90/100/110/120/130/140/150 s.

Basic unit

Safety outputs		Auxiliary outputs	The second secon	3	Terminal block type	Order code
Instantaneous	OFF-delayed		channels			
2 P channel MOS FET	_	2 PNP transistor 1 or 2 channels 24 VDC	24 VDC	Screw terminals	G9SX-BC202-RT	
transistor output	output	Cage clamp terminals	G9SX-BC202-RC			

Expansion unit

Safety outputs		Auxiliary outputs	OFF-delay time Rated voltage	Rated voltage	Terminal block type	Order code
Instantaneous	OFF-delayed					
4 PST-N0 (contact)		2 (solid state) PNP transistor outputs	-		Screw terminals	G9SX-EX401-RT
					Cage clamp terminals	G9SX-EX401-RC
-	4 PST-N0 (contact)		Synchronized with G9S-X-AD - unit		Screw terminals	G9SX-EX041-T-RT
					Cage clamp terminals	G9SX-EX041-T-RC

Specifications

Power input				Inputs		
Item	G9SX-AD_	G9SX-BC202	G9SX-EX	Item	G9SX-AD_	G9SX-BC202
Rated supply voltage	supply voltage 20.4 to 26.4 VDC (24 VDC -15% +10%)				Operating voltage: 20.4 VDC to 26.4 VDC,	
				Feedback/reset input	internal impedance: Approx. 2.8 k Ω	

Outputs

Item	G9SX-AD_	G9SX-BC202	
Instantaneous safety output OFF-delayed safety output	P channel MOS FET transistor output Load current: Using 2 outputs or less: 1 A DC max. Using 3 outputs or more: 0.8 A DC max.	P channel MOS FET transistor output Load current: Using 1 output: 1 A DC max. Using 2 outputs: 0.8 A DC max.	
Auxiliary output	PNP transistor output		

Expansion unit

Item	G9SX-EX
Rated load	250 VAC, 3A/30 VDC, 3A (resistive load)
Rated carry current	3 A
Maximum switching voltage	250 VAC, 125 VDC
Characteristics	

Item		G9SX-AD_	G9SX-BC202	G9SX-EX
Operating time (OFF to ON state)		50 ms max. (Safety input: 0N) 50 ms max. (Safety input: 0N) 100 ms max. (Logical AND connection input: 0N)		30 ms max.
Response time (ON to OFF state)		15 ms max.	10 ms max.	
Durability Electrical		-		100,000 cycles min.
Mechanical		-		5,000,000 cycles min.
Ambient temperature		-10°C +55°C (with no icing or condensation)		





Standstill monitoring unit

Safe standstill monitoring unit based on Back-EMF operation for two- and three-phase systems.

- Ready to use covering all standard applications without additional setup
- · Easy integration in star- and delta wiring
- Clear LED diagnosis of all in- and output signals for easy maintenance
- Applicable up to Safety Category 4 according to EN954-1

Ordering information

Safety standstill monitoring unit

Safety outputs *1 Instantaneous	Auxiliary outputs *1	Power input Rated supply voltage	Terminal block type	Order code
3 (Semi-conductors) 2 (Semi-conductors	2 (Semi-conductors)	24 VDC Screw terminals 0	G9SX-SM032-RT	
			Spring-cage terminals G9SX-	G9SX-SM032-RC

^{*1} PNP transistor output

Specifications

Rated supply voltage

Ratings of non-contact door switch controllers

G9SX-SM032-

24 VDC

Power input

Inputs	
Item	G9SX-SM032
Input voltage	Standstill detection input (Z1-Z2/Z3-Z4) AC 415 Vrms + 10% max.
Maximum power supply frequency for AC induction motor	60 Hz max.
Internal impedance	Standstill detection input: approx, $660~\text{k}\Omega$ EDM input: approx. $2.8~\text{k}\Omega$


Outputs


Item	G9SX-SM032
	Sourcing output (PNP) Load current: 300 mA DC max.
	Sourcing output (PNP) Load current: 100 mA DC max.

Application example

3-phase motor

Standstill detected





Standstill detected

3-phase motor with star-delta wiring





Limited speed monitoring unit

Safe limited speed monitoring unit for complete support of maintenance mode in machinery.

- Preset of limited speed frequency by using integrated preset switches
- Easy integration in G9SX-Systems by using unique logical "AND" connection
- Clear LED diagnosis of all in- and output signals for easy maintenance
- Applicable up to safety category 3 according to EN954-1 using Omron proximity

Ordering information

Proximity sensors			
Classification			Order code
Proximity sensor	Shielded	M8	E2E-X1R5F1
		M12	E2E-X2F1
		M18	E2E-X5F1
	Unshielded	M8	E2E-X2MF1
		M12	E2E-X5MF1
		M18	F2F-X10MF1

Safety standstill monitoring unit

Safety outputs *1 Instantaneous	Auxiliary outputs *2	Logical AND connection input	Rated voltage	Sensor power supply terminals	Terminal block type	Order code
4 (Semi-conductors)	4 (Semi-conductors)	1	24 VDC	2	Screw terminals	G9SX-LM224-F10-RT
					Spring-cage terminals	G9SX-LM224-F10-RC

^{*1} P channel MOS FET output *2 PNP transistor output

Specifications

Ratings of non-contact door switch controllers


Power input

Item	G9SX-LM224-F10			
Rated supply voltage	24 VDC			
Inputs				
Item	G9SX-LM224-F10			
Safety input	Operating voltage: 20.4 VDC to 26.4 VDC			
Feedback/reset input	Internal impedance: approx. 2.8 k Ω			
Mode selector input				
Rotation detection input	Operating voltage 20.4 VDC to 26.4 VDC Internal impedance: approx. 2.8 k Ω Input frequency: 1 kHz max.			
Outputs				
Item	G9SX-LM224-F10			
Safety solid state output	P channel MOS FET transistor output Load current: 0.8 A DC max.			
Safety speed detection output	P channel MOS FET transistor output Load current: 0.3 A DC max.			
External indicator output	PNP transistor output Load current: 100 mA max.			



Application example

Safe limited speed





Standalone safety controller

The G9SP safety controller provides all local safety based in- and outputs and controls the safety application.

- Three CPU-types to suit different applications
- Clear diagnosis and monitoring via Ethernet or serial connection
- Memory cassette for easy duplication of configuration
- Unique programming software to support easy design, verfication, standardization and reusage of the program.
- Certified according to PLe (EN ISO 13849-1) and SIL 3 (IEC 61508)

Ordering information

Appearance	Appearance description	Order code
Standalone safety controller	10 PNP safety inputs 4 PNP safety outputs 4 test outputs 4 PNP standard outputs	G9SP-N10S
	10 PNP safety inputs 16 PNP safety outputs 6 test outputs	G9SP-N10D
	20 PNP safety inputs 8 PNP safety outputs 6 test outputs	G9SP-N20S

Software

Appearance	Media	Applicable OS	Order code
G9SP configurator	Setup disk 1 license	Windows 2000 Windows XP Windows Vista	WS02-G9SP01-V1
	Setup disk 10 licenses		WS02-G9SP10-V1
	Setup disk 50 licenses		WS02-G9SP50-V1
	Setup disk Site license		WS02-G9SPXX-V1

Expansion units (standard I/0)


Appearance	Туре	Number of I/O		Model
		In	Out	
Expansion I/O unit	Sinking	12	8 (solid state)	CP1W-20EDT
	Sourcing	12	8 (solid state)	CP1W-20EDT1
	Sinking	-	32 (solid state)	CP1W-32ET
	Sourcing	-	32 (solid state)	CP1W-32ET1
I/O Connecting cable, 80 cm long CP1W-CN811			CP1W-CN811	

Option units

Appearance	Order code
RS-232 option board	CP1W-CIF01
Ethernet option board (Ver. 2.0 or later)	CP1W-CIF41
Memory cassette	CP1W-MF05M

G9SP configuration

- Safety controller G9SP
- Expansion I/O units
- Memory cassette
- Ethernet option board
- 6 RS-232C option board 6 Compact non-contact door switch
- Safety mats



Specifications

General specifications

Power supply voltage		20.4 to 26.4 VDC (24 VDC -15% +10%)
Consumption current	G9SP-N10S	400 mA (V1: 300 mA, V2: 100 mA)
	G9SP-N10D	500 mA (V1: 300 mA, V2: 200 mA)
	G9SP-N20S	500 mA (V1: 400 mA, V2: 100 mA)
Mounting metho	d	35-mm DIN track
Ambient operating temperature		0°C +55°C
Ambient storagetemperature		-20°C +75°C
Degree of protection		IP20 (IEC 60529)

Safety input specifications

Input type	Sinking inputs (PNP)
ON voltage	11 VDC min. between each input terminal and G1
OFF voltage	5 VDC max. between each input terminal and G1
OFF current	1 mA max.
Input current	6 mA

Safety output specifications

Output type	Sourcing outputs (PNP)
Rated output current	0.8 A max. per output*
Residual voltage	1.2 V max. between each output terminal and V2
Residual voltage	1.2 V max. between each output terminal and V2

Test output specifications

Output type	Sourcing outputs (PNP)
Rated output current	0.3 A max. per output*
Residual voltage	1.2 V max. between each output terminal and V1

Standard output specifications (G9SP-N10S)

Output type	Sourcing outputs (PNP)
ON Residual voltage	1.5 V max. (between each output terminal and V2)
Rated output current	100 mA max.*

*For details on the rated output current, please refer to the user manual of G9SP.



Control system integration Safety - I/O-status becomes transparent The standalone safety controller offers diagnosis information in 3 ways: 1) via parallel wiring 2) via serial RS232C interface (option) 3) via Ethernet interface (option). Information of all safety in- and outputs on the standard control system ensure minimum downtime of the machine. Machine control Safety control G9SP Standalone safety controller Serial RS232C Ethernet


switch

Safety light

G9SP configuration tool




Easy setup and configuration is provided by a setup wizard supporting the hardware selection.



Integrated Simulator

All functions can be tested and simulated in the configuration tool, so there's no unnecessary additional workload for the engineer. In addition, on-line diagnosis reduces debug time to a minimum during implementation in the machine control system.






Emergency

User-defined function blocks

Contactor

Approved configuration elements such as a tested door monitoring solution can be easily stored as a user defined function block and re-used in future projects. This minimises the time it takes to create a new system configuration.



Knowledge-building

Existing configurations are the basis for new projects. The G9SP configuration tool supports re-use of existing and proven know-how in safety control, as well as user-defined function blocks. Which means no more repetition of effort, instead a growing library of safety solutions.





Safety network controller

The NE1A hosts the safety application program. All local and DeviceNet safety-based in- and outputs are monitored and controlled by the NE1A. It manages up to 32 DeviceNet safety slaves and can be seamlessly integrated in a standard DeviceNet system.

- · Removable cage-clamp terminals for easy installation
- · Predefined and certified function blocks for easy programming
- · LED display and status LEDs for advanced diagnostics
- System status on DeviceNet for easy troubleshooting and predictive maintenance
- Easy scalability through the addition of DeviceNet safety devices

Ordering information

Appearance	Appearance description	Interface	Order code
Safety network controler	8 PNP outputs 4 test outputs 254 function block programming	USB and DeviceNet safety	NE1A-SCPU01-V1
		Ethernet/IP and DeviceNet safety	NE1A-SCPU01-EIP
	40 PNP inputs 8 PNP outputs 8 test outputs 254 function block programming removable cage clamp terminals	USB and DeviceNet safety	NE1A-SCPU02
		Ethernet/IP and DeviceNet safety	NE1A-SCPU02-EIP

Software

Appearance	Appearance description	Order code
configurator	Installation disk (CD-ROM) IBM PC/AT compatible Windows 2000 or XP (English version)	WS02-CFSC1-E

Accessories

Appearance	Appearance description	Order code
Network router	Ethernet/IP - DeviceNet router	NE1A-EDR01
Programming console	CF-Card slot to store configuration USB-Interface for maintenance Touchscreen for easy troubleshooting	NE1A-HDY

Specifications

General specifications

DeviceNet comm	unications power supply voltage	11 to 25 VDC (supplied from communications connector)
Unit power supply voltage		20.4 to 26.4 VDC
I/O power supply voltage		(24 VDC -15% +10%)
Consumption current	Communications power supply	24 VDC, 15 mA
	Internal circuit power supply	24 VDC, 230 mA
Mounting method		35-mm DIN track
Ambient operating temperature		-10°C +55°C
Ambient storage temperature		-40°C +70°C
Degree of protection		IP20 (IEC 60529)

Safety input specifications

Input type	Sinking inputs (PNP)
ON voltage	11 VDC min. between each input terminal and G1
OFF voltage	5 VDC max. between each input terminal and G1
OFF current	1 mA max.
Input current	4.5 mA

Safety output specifications

Output type	Sourcing outputs (PNP)
Rated output current	0.5 A max. per output
Residual voltage	1.2 V max. between each output terminal and V2

Test output specifications

Output type	Sourcing outputs (PNP)
Rated output current	0.7 A max. per output (see note.)
Residual voltage	1.2 V max. between each output terminal and V1






DeviceNet safety I/O terminal block family

- · Removable cage clamp terminals for easy installation
- Up to 12 inputs for safety signals
- 4 test pulse outputs to ensure crosstalk and short circuit detection
- Up to 8 safety outputs (solid state or relay)
- · Status LEDs for advanced diagnostics
- · Mixed mode operation (safety and standard) for all in- and outputs

Ordering information



Appearance	Appearance description	Order code
Input terminal	12 PNP inputs 4 Test outputs Removable cage clamp terminals	DST1-ID12SL-1
Mixed I/O terminal	8 PNP inputs 8 PNP outputs 4 Test outputs Removable cage clamp terminals	DST1-MD16SL-1
Mixed I/O terminal	4 PNP inputs 4 relay outputs (4×2-single pole) 4 Test outputs Removable cage clamp terminals	DST1-MRD08SL-1



Specifications

General specifications DeviceNet communications power 11 to 25 VDC (supplied from communications connector) supply voltage 20.4 to 26.4 VDC (24 VDC -15% +10%) Unit power supply voltage I/O power supply voltage Consumption current Communications power supply DST1-ID12SL-1/MD16SL-1: 100 mA DST1-MRD08SL-1: 110 mA **Mounting method** 35-mm DIN track Ambient operating temperature -10°C +55°C -40°C +70°C Ambient storage temperature IP20 (IEC 60529) Degree of protection DST1-ID12SL-1/MD16SL-1: 420 g Weight DST1-MRD08SL-1: 600 g

Safety input specifications

Input type	Sinking inputs (PNP)
ON voltage	11 VDC min. between each input terminal and G1
OFF voltage	5 VDC max. between each input terminal and G1
OFF current	1 mA max.
Input current	6 mA

Safety output specifications

Output type	Sourcing outputs (PNP)		
Rated output current	0.5 A max. per output		
Residual voltage	1.2 V max. between each output terminal and V1		

Test output specifications


Output type	Sourcing outputs (PNP)
Rated output current	0.7 A max. per point
Residual voltage	1.2 V max. between each output terminal and V0

Safety output specifications for relay outputs


,pp	,,
Relays	G7SA-2A2B, EN 50205 class A
Minimum applicable load	1 mA at 5 VDC
Rated load for a resistive load	240 VAC: 2 A, 30 VDC: 2 A
Rated load for an inductive load	2 A at 240 VAC (cosφ= 0.3), 1 A at 24 VDC
Mechanical life expectancy	5,000,000 operations min. (switching frequency of 7,200 operations/h)
Electrical life expectancy	100,000 operations min. (at rated load and switching frequency of 1.800 operations/h)

Safety I/O terminals






DST1-MD16SL-1



DST1-MRD08SL-1







Relays with forcibly guided contacts

The slim G7SA relay family with forcibly guided contacts is available as a fouror six-pole type in various contact combinations and offers reinforced insulation. Terminals are arranged for easy PCB layout. It can be soldered directly to a PCB or used together with the P7SA sockets.

- · Forcibly guided contacts
- Conforms to EN 50205
- . 6 A at 240 VAC and 6A at 24 VDC for resistive loads
- Reinforced insulation between inputs and outputs and poles
- 4- and 6-pole relays available

Ordering information

Relays with 1	forcibly	guided	contacts

Туре	Sealing	Poles	Contacts	Rated voltage	Order code
Standard	Flux-tight	4 poles	3PST-NO, SPST-NC		G7SA-3A1B
			DPST-NO, DPST-NC		G7SA-2A2B
		6 poles	5PST-NO, SPST-NC		G7SA-5A1B
			4PST-NO, DPST-NC		G7SA-4A2B
			3PST-NO, 3PST-NC		G7SA-3A3B

Sockets							
Туре		LED indicator	Poles	Rated voltage	Order code		
Track-mountining Track mounting and screw mounting possible	Track mounting	Yes	4 poles	24 VDC	P7SA-10F-ND		
	mounting		6 poles		P7SA-14F-ND		
Back-mounting	PCB terminals	No	4 poles	-	P7SA-10P		
			6 poles		P7SA-14P		

Specifications

Rated voltage	Rated current	Coil resistance	Must-operate voltage	Must-release voltage	Max. voltage	Power consumption
24 VDC	4 poles: 15 mA 6 poles: 20.8 mA	4 poles: 1,600 Ω 6 poles: 1,152 Ω	75% max. (V)	10% min. (V)	` '	4 poles: Approx. 360 mW 6 poles: Approx. 500 mW

Note: Refer to datasheet for details

Contacts

Load	Resistive load ($cos\phi = 1$)
Rated load	6 A at 250 VAC, 6 A at 30 VDC
Rated carry current	6 A
Max. switching voltage	250 VAC, 125 VDC

Load	Resistive load ($cos\phi = 1$)
Max. switching current	6 A
Max. switching capacity (reference value)	1,500 VA, 180 W

Relays with forcibly guided contacts

Contact resistance		100 m Ω max. (The contact resistance was measured with 1 A at 5 VDC using the voltage-drop method.)				
Operating time *1		20 ms max.				
Response time *1		10 ms max. (The response time is the time it takes for the normally open contacts to open after the coil voltage is turned OFF.)				
Release time *1		20 ms max.				
Insulation resistance		100 M Ω min. (at 500 VDC) (The insulation resistance was measured with a 500 VDC megger at the same places that the dielectric strength was measured.)				
Dielectric strength *2 *3		Between coil contacts/different poles: 4,000 VAC, 50/60 Hz for 1 min (2,500 VAC between poles 3-4 in 4-pole Relays or poles 3-5, 4-6, and 5-6 in 6-pole Relays.) Between contacts of same polarity: 1,500 VAC, 50/60 Hz for 1 min				
Durability	Mechanical	10,000,000 operations min. (at approx. 36,000 operations/hr)				
Electrical		100,000 operations min. (at the rated load and approx. 1,800 operations/hr)				
Min. permissible load	I ^{*4}	5 VDC, 1 mA (reference value)				
Ambient temperature	*5	Operating: -40 to 85°C (with no icing or condensation)				
Ambient humidity		Operating: 35 to 85%				
Approved standards		EN61810-1 (IEC61810-1), EN50205, UL508, CSA22.2 No. 14				

- These times were measured at the rated voltage and an ambient temperature of 23°C. Contact bounce time is not included.
- These times were measured at the race voltage and an ambient emperature of 25 or contact bounds which is not measured.

 13 When using a P7SA socket, the dielectric strength between coil contacts/different poles is 2,500 VAC, 50/60 Hz for 1 min.

 14 Min. permissible load is for a selectioning frequency of 300 operations/min.

 15 When using a P7SA socket, the dielectric strength between coil contacts/different poles is 2,500 VAC, 50/60 Hz for 1 min.

 16 When using a P7SA socket, the dielectric strength between coil contacts/different poles is 2,500 VAC, 50/60 Hz for 1 min.

 17 When using a P7SA socket, the dielectric strength between coil contacts/different poles is 2,500 VAC, 50/60 Hz for 1 min.

- *5 When operating at a temperature between 70°C and 85°C, reduce the rated carry current (6 A at 70°C or less) by 0.1 A for each degree above 70°C.

Note: The values listed above are initial values.



 $^{^{\}star1}~$ 12 VDC, 21 VDC, 48 VDC are available on request.

Reliability data of Omron components

Below tables show the reliability data of Omron components and give a reference to the relevant standard:

Emergency stop switches

Model name	B _{10d}	Remarks
A165E	100.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
A22E	100.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
ER5018	1.500.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
ER6022	1.500.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed. Additionally valid for all XER and stainless steel models
ER1022	1.500.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed. Additionally valid for all XER models
ER1032	1.500.000	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed. Additionally valid for all XER models

Safety limit switches

Model name	B _{10d}	Remarks
D4BN*1	2.000.000	From table in annex C of EN ISO 13849-1
D4N*1	2.000.000	From table in annex C of EN ISO 13849-1
D4NH ^{*1}	2.000.000	From table in annex C of EN ISO 13849-1
D4NR*1	2.000.000	From table in annex C of EN ISO 13849-1
D4F*1	2.000.000	From table in annex C of EN ISO 13849-1

^{*1} If fault exclusion for direct opening action of NO and NC is possible.

Safety door switches

Model name	B _{10d}	PL	Category	MTTF _d	DC	Remarks
D4NL	2.000.000	n.a.	n.a.	n.a.	n.a.	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
D4GL*1	2.000.000	n.a.	n.a.	n.a.	n.a.	From table in annex C of EN ISO 13849-1
D4BL*1	2.000.000	n.a.	n.a.	n.a.	n.a.	From table in annex C of EN ISO 13849-1
D4NS	2.000.000	n.a.	n.a.	n.a.	n.a.	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
D4BS*1	2.000.000	n.a.	n.a.	n.a.	n.a.	From table in annex C of EN ISO 13849-1
F3S-TGR-N_C	3.300.000	n.a.	n.a.	n.a.	n.a.	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
F3S-TGR-N_R	3.300.000	n.a.	n.a.	n.a.	n.a.	Adopted EN ISO 13849-1 Annex C, B _{10d} fixed
D40A + G9SX-NS	n.a.	d	3	100 years	95%	Adopted EN ISO 13849-1 Annex C, PL data fixed

^{*1} If fault exclusion for direct opening action is possible.

Safety sensors

Model name	B _{10d}	PL	Category	MTTF _d	DC	Remarks
MS2800E_	n.a.	С	2	51 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
MS4800E_	n.a.	е	4	51 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
F3S-TGR-CL2_	n.a.	С	2	450 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
F3S-TGR-CL4_	n.a.	е	4	450 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed

Safe control systems

Model name	B _{10d}	PL	Category	MTTF _d	DC	Remarks
G9SA-301	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SA-300-SC	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SB-series*1	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SB-3010	n.a.	d	3	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SP-N10S	n.a.	е	4	n.a.	n.a.	PFHd = 7,80E-11
G9SP-N10D	n.a.	е	4	n.a.	n.a.	PFHd = 9,96E-11
G9SP-N20S	n.a.	е	4	n.a.	n.a.	PFHd = 8,55E-11
G9SX-BC	n.a.	е	4	100 years	97%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SX-AD	n.a.	е	4	100 years	97%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SX-ADA	n.a.	е	4	100 years	97%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SX-EX	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SX-SM	n.a.	е	4	100 years	98%	Adopted EN ISO 13849-1 Annex C, PL data fixed
G9SX-LM	n.a.	d	3	100 years	82%	Adopted EN ISO 13849-1 Annex C, PL data fixed
NE1A-SCPU01	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
NE1A-SCPU02	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
NEOA-SCPU01	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
DST1-ID12SL-1	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
DST1-MD16SL-1	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
DST1-MRD08SL-1	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed
DST1-XD0808SL-1	n.a.	е	4	100 years	99%	Adopted EN ISO 13849-1 Annex C, PL data fixed

^{*1} Except G9SB-3010



Reliability data of Omron components

Safe actuators

Model name	B _{10d}	Remarks
G7SA*1	400.000	According to IEC 61810-1, valid for DC13, Inductive load le
G7SA*1	400.000	According to IEC 61810-1, valid for DC13, Inductive load le/2
G7SA*1	400.000	According to IEC 61810-1, valid for DC13, Inductive load le/4
G7SA*1	400.000	According to IEC 61810-1, valid for AC15 load

 $^{^{\}star}1$ $\,$ Refer to the load characteristic to select correct B_{10d} value

Please check Omron in the Internet for updated information: http://industrial.omron.eu/safety

Further information can be found in the SISTEMA library: http://industrial.omron.eu/safety

